

3444 Triplett

Roll Chart Supplement

(To Roll Chart 84-95-061463-7)

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
00A . . .	5.0	8.5	1450-0-2000	6	1	.43/.66	F
01A . . .	5.0	6	1450-0-2000	6	1	.47/.73	F
0Y4 . . .	0	33	0090-4-0210	4	8	Rect.	F (1)
	—	14	— — —	—	—	Rect.	F (2)
1A4 . . .	2.0	7	1460-0-2000	6	1	.47/.73	F (7)
1A5 . . .	1.4	7	0146-5-0200	6	1	.55/.85	F
1A6 . . .	2.0	20	1445-6-2000	8	1	.40/.80	F (7)
1AB5 . . .	1.4	30	1460-0-5220	5	2	.89/1.4	F
1B1 . . .	2.35	0	1000-0-3000	11	8	*	
Switch SHORTS-LEAKAGE switch to H-K position							
* Good tube indicates to full scale.							
1B4P . . .	2.0	29	1460-0-2000	8	1	.34/.52	F (7)
1B5 . . .	2.0	20	1400-5-2000	5	1	.37/.57	F (1)
	—	0	1049-0-2000	11	8	Diode	F (1)(2)
1C5 . . .	1.4	10	0146-5-0200	6	2	.95/1.5	F
1C6 . . .	2.0	20	1445-6-2000	8	2	.45/.90	F (7)
1C7 . . .	2.0	20	0146-5-4200	8	2	.45/.90	F (7)
1C21 . . .	—	0	0300-4-0550	2	7	* Thyratron	
* Reject at 15 on Rect. Scale							
1D5 . . .	2.0	9	0146-0-0200	8	1	.46/.71	F (7)
1D7 . . .	2.0	20	0146-5-4200	8	2	.40/.80	F (7)
1D8 . . .	1.4	12	0146-5-0290	6	2	.65/1.0	F (1)
	—	—	0100-0-4290	5	1	.40/.61	F (1)(7)
	—	0	— — —	11	8	Diode	F (2)
1E4 . . .	1.4	5	0140-5-0200	6	1	.55/.85	F
1E7 . . .	2.0	10	029X-5-4160	5	2	.90/1.4	F (1)(2)
This set up to be used on tester above serial #5000							
1E7* . . .	2.0	50	029X-5-4160	5	2	.90/1.4	F (1)(2)
* This set up must be used on tester below serial #5000							
1F4 . . .	2.0	6	1450-6-2000	5	2	.91/1.4	F
1F5 . . .	2.0	6	0146-5-0200	5	2	.91/1.4	F
1F6 . . .	2.0	9	1460-0-2000	3	1	.42/.65	F (7)
	—	0	1004-9-2000	11	8	Diode	F (1)(2)
1F7 . . .	2.0	8	0140-0-6200	3	1	.42/.65	F (7)
	—	0	0104-9-0200	11	8	Diode	F (1)(2)
1G4 . . .	1.4	8	0140-5-0200	6	1	.54/.83	F
1G5 . . .	2.0	10	0146-5-0200	6	2	.98/1.5	F
1G6 . . .	1.4	10	0145-X-9200	5	1	.44/.68	F (1)(2)
1H4 . . .	2.0	7	0140-5-0200	6	1	.55/.85	F
1H6 . . .	2.0	22	0140-0-5200	5	1	.37/.57	F
	—	0	0104-9-0200	11	8	Diode	F (1)(2)

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
1J5	2.0	12	0146-5-0200	6	2	.61/.94	F
1J6	2.0	0	0145-X-9200	5	2	.85/1.3	F (1)(2)
1V	6.3	14	2430-0-1000	6	8	Rect.	
2A3	2.8	40	1450-0-2000	2	3	2.6/5.2	F
2A5	2.8	16	1465-3-2000	2	2	1.1/2.2	
2A6	2.8	20	1400-3-2000	1	2	.72/1.1	(1)(7)
	-	0	1049-3-2000	11	8	Diode	(1)(2)
2C36	6.3	12	1254-0-0000	2	3	2.2/4.5	F
			Adapter CG or CM				
2C39	6.3	4	1254-0-0000	1	3	3.0/6.0	F
			Adapter CG or CN				
2-01C	5.0	0	1200-0-0000	11	8	Diode	F (6)
			Adapter CG or Leads				
2X2	2.8	9	1000-0-2000	4	8	Rect.	F (6)
2Y2	2.8	11	1000-0-2000	4	8	Rect.	F (6)
2Z2	2.8	11	1400-0-2000	5	8	Rect.	F (6)
3E29	6.3	5	1563-2-5100	3	4	7.0/14.	(6)
			Adapter CG or CM (Connect two plate terminals with jumper)				
4HS8	4.2	18	3641-2-7547	5	2	1.3/2.0	
4-65A	6.3	15	1605-0-6200	2	2	1.2/2.4	(6)
			Adapter CG or CM				
5BC3	5.0	12	1020-9-0004	6	8	Rect.	F(1)(2)
			Adapter CL—Connect side pin to Plate cap				
5X3	5.0	11	1940-0-2000	6	8	Rect.	F (1)(2)
6A3	6.3	11	1450-0-2000	6	3	2.3/4.5	F
6A4	6.3	8	1450-6-2000	6	2	1.1/2.2	F
6BE3	6.3	0	1400-3-0042	11	8	Diode	
			Adapter CK				
6DS4	6.3	1	4531-2-0000	9	3	5.3/8.2	
			Below serial #3000 use Adapter CI				
6DW4	6.3	14	0401-2-0403	6	8	Rect.	
			Adapter CL—Connect side pin to Cath. Cap				
6FM7	6.3	29	1090-8-X352	4	2	1.7/2.2	(1)
	-	11	— — —	6	3	2.8/5.6	(3)
			Adapter CK—Connect Plate Cap to C				
6FY7	6.3	29	8541-0-20X9	4	2	1.0/1.6	(1)
	-	12	— — —	6	3	3.6/5.4	(3)
			Adapter CK—Rotate tube so that arrow is at pin 6				
			Connect B to Cath. Cap				
6GJ5	6.3	18	6531-2-5600	3	3	3.0/6.0	(6)
			Adapter CL				
6GJ7/	6.3	9	3531-2-469X	5	4	7.2/11.	(1)
ECF801	-	29	— — —	-	3	6.0/9.0	(2)
6GT5	6.3	16	6531-2-5604	3	3	3.4/6.8	
			Adapter CL—Connect Plate Cap to side pin on Adapter				
6HA5/							
EC900	6.3	8	5312-4-0300	5	4	7.2/11.	
6HE5	6.3	18	1304-0-0562	2	3	2.0/4.1	
			Adapter CK				

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
6R4	6.3	20	5031-2-0040	5	3	3.1/4.6	
6HR6	6.3	9	5712-4-6300	4	3	5.0/7.6	
6JU8	6.3	0	4301-2-0980	11	8	Diode	(1)(3)
			0431-2-0098	11	8		(1)(3)
6K4	6.3	18	4510-0-2030	5	3	3.3/5.0	
6Y5	6.3	13	1093-4-2000	6	8	Rect.	(1)(2)
6Z4	6.3	12	1940-3-2000	6	8	Rect.	(1)(2)
6Z5	6.3	14	2193-4-1000	6	8	Rect.	(1)(2)
7G8	6.3	27	196X-5-3420	4	2	1.4/2.1	(1)(2)
			This set up to be used on tester above serial #5000				
7G8*	6.3	20	196X-5-3420	4	2	1.4/2.1	(1)(2)
			* This set up must be used on tester below serial #5000				
10	7.5	22	1450-0-2000	3	2	.91/1.4	F
10JY8	10.5	19	8X91-2-3564	4	4	5.5/11	(1)
		7	— — —	5	3	6.0/9.2	(3)
10Y	7.5	19	1450-0-2000	2	2	1.0/1.6	F
12A	5.0	12	1450-0-2000	6	1	1.2/1.9	F
12G8	6.3	19	98X1-1-4352	11	2	1.8/2.6	(1)
		4	— — —	—	—	—	(3)
12GJ5	12.6	18	6531-2-5600	3	3	3.0/6.0	(6)
			Adapter CL				
12GT5	12.6	16	6531-2-5604	3	3	3.4/6.8	
			Adapter CL—Connect Plate cap to side pin on Adapter				
14	12.6	7	1460-3-2000	3	2	.65/1.0	(7)
15	2.0	44	1460-3-2000	5	1	.47/.71	(7)
17	12.6	20	1450-3-2000	2	2	.65/1.0	
17GJ5	16.8	18	6531-2-5600	3	3	3.0/6.0	(6)
			Adapter CL				
17GT5	16.8	16	6531-2-5604	3	3	3.4/6.8	
			Adapter CL—Connect Plate cap to side pin on Adapter				
19	2.0	21	19X5-4-2000	5	2	.65/1.0	F
19HR6	18.9	9	5712-4-6300	4	3	5.0/7.6	
20	3.15	11	1450-0-2000	6	1	.34/.53	F
22	3.15	25	1460-0-2000	8	1	.33/.50	F (7)
24A	2.8	6	1460-3-2000	3	2	.68/1.1	(7)
25Y5	26.0	12	1983-4-2000	6	8	Rect.	(1)(3)
26	1.4	9	1450-0-2000	6	1	5.8/9.0	F
27	2.35	20	1450-3-2000	2	2	.63/.97	
29	2.35	10	1453-3-2000	5	2	.52/.80	(1)
			1435-3-2000	—	—	—	(1)
30	2.0	20	1450-0-2000	2	2	.58/.90	F
31	2.0	47	1450-0-2000	2	2	.65/1.0	F
32	2.0	12	1460-0-2000	3	1	.42/.65	F (7)
33	2.0	32	1450-6-2000	2	2	.90/1.7	F
34	2.0	11	1460-0-2000	3	1	.40/.62	F (7)
35	2.5	6	1460-3-2000	3	2	.65/1.0	(7)
36	6.3	16	1460-3-2000	8	2	.55/.85	(7)
37	6.3	7	1450-3-2000	7	2	.59/.90	
38	6.3	10	1460-3-2000	6	1	.57/.87	(7)
41	6.3	8	1465-3-2000	6	2	.75/1.5	
42	6.3	17	1465-3-2000	2	2	1.3/2.5	

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
43	26.0	16	1465-3-2000	6	2	1.0/2.0	
45	2.8	45	1450-0-2000	2	2	1.1/2.2	F
46	2.8	32	1450-4-2000	2	2	1.2/2.4	F
47	2.8	19	1450-6-2000	2	2	1.3/2.5	F
48	35.0	19	1465-3-2000	6	3	1.9/3.8	
50	7.5	34	1450-0-2000	2	2	.95/1.9	F
52	6.3	0	1450-6-2000	5	3	1.4/2.7	F
55	2.8	19	1400-3-2000	2	2	.71/1.1	(1)(7)
	-	0	1094-3-2000	11	8	Diode	(1)(2)
56	2.8	6	1450-3-2000	6	2	.71/1.1	
57	2.8	34	1467-3-2000	5	2	.78/1.2	(7)
57AS	6.3	36	1467-3-2000	4	2	.78/1.2	(7)
58	2.8	35	1467-3-2000	5	2	.98/1.5	(7)
64	6.3	6	1460-3-2000	3	2	.71/1.1	(7)
65	6.3	6	1460-3-2000	3	2	.65/1.0	(7)
67	6.3	19	1450-3-2000	2	2	.59/.90	
68	6.3	14	1460-3-2000	6	2	.71/1.1	(7)
HY69	6.3	23	1650-7-2000	2	2	1.5/2.9	F (6)
71A	5.0	19	1450-0-2000	6	2	.85/1.7	F
75	6.3	22	1400-3-2000	4	2	.71/1.1	(7)
	-	0	1094-3-2000	11	8	Diode	(1)(2)
76	6.3	6	1450-3-2000	6	2	.78/1.2	
77	6.3	14	1467-3-2000	8	2	.71/1.1	(7)
78	6.3	17	1467-3-2000	5	2	1.0/1.6	(7)
80	5.0	10	1940-0-2000	6	8	Rect.	F (1)(3)
85	6.3	8	1400-3-2000	6	2	.72/1.1	(1)(7)
	-	0	1094-3-2000	11	8	Diode	(1)(2)
286A	2.0	35	1467-3-2000	5	2	.78/1.2	(7)
CK544DX	1.25	29	4615-2-0000	9	1	.22/.33	* F
(* No Leakage Test)							
801	6.3	17	1450-0-2000	2	2	1.2/1.8	F
807	6.3	23	1650-3-2000	2	3	1.6/3.2	(6)
809	6.3	22	1050-0-2000	1	2	.80/1.6	F (6)
812	6.3	7	1050-0-2000	2	2	.80/1.6	F (6)
816	2.8	12	1000-0-2000	6	8	Rect.	F (6)
829B	6.3	5	1563-2-5100	3	4	7.0/14.	(6)
Adapter CG or CM (Connect two plate terminals with jumper)							
832-A	6.3	8	1563-2-5100	3	3	3.5/7.0	(6)
Adapter CG or CM (Connect two plate terminals with jumper)							
840	2.0	9	1657-0-2000	3	1	.26/.40	F (6)
841	7.5	0	1450-0-2000	2	2	.65/1.0	F
842	7.5	38	1450-0-2000	2	2	.65/1.3	F
864	1.25	6	1450-0-2000	6	1	.42/.65	F
866	2.8	12	1000-0-2000	6	8	Rect.	F (6)
874	6.3	0	2040-0-0000	5	6	*	(1)
(* No Leakage Test)							
Increase A to 26.0, firing is indicated by upscale deflection							

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
885	2.8	40	1450-3-2000	3	7	* Thyratron (* Fires from 40-10; cuts off from 10-40)	
950	2.0	13	1450-6-2000	6	1	.62/.95	F
951	2.0	0	1460-0-2000	5	2	.39/.60	F (7)
1006	2.0	32	1940-0-2000	4	8	Rect.	F (1)(2)
1229	2.0	12	1460-0-2000	3	1	.42/.65	F (7)
1609	1.4	5	1450-6-2000	8	1	.47/.72	F
1624	2.8	12	1650-0-2000	2	3	2.0/4.0	F (6)
5633	6.3	16	3751-6-2000	5	3	2.2/3.4	(6)
5634	6.3	12	3751-6-2000	5	3	2.3/3.5	(6)
5635	6.3	11	X510-4-2930	5	3	2.5/3.8	(1)(2)
5646	6.3	11	4315-2-0000	5	2	1.6/2.4	
5656	6.3	9	65X1-2-3943	5	3	3.8/5.8	(1)(2)
5742	4.7	6	1450-0-2000	2	1	.56/.85	F
5784	6.3	13	4612-7-3500	5	3	2.1/3.2	
5825	1.4	0	1000-0-2000	1	8	Diode	F (6)
5894	6.3	7	1563-2-5100	3	4	6.5/13.	(6)
Adapter CG or CM (Connect two plate terminals with jumper)							
5904	26.0	12	5010-3-2040	9	3	3.0/4.7	
5905	26.0	7	5313-4-2630	9	3	1.9/2.9	
5907	26.0	6	5313-4-2630	9	2	2.0/3.0	
5908	26.0	17	5317-4-2630	9	2	1.5/2.2	
5998	6.3	8	543X-9-8120	6	4	7.5/13.	(1)(3)
6094	6.3	10	5614-2-5634	2	3	2.6/4.1	
6247	6.3	23	5514-3-2040	1	2	1.7/2.6	
6263	6.3	40	1235-4-0000	1	3	3.5/7.0	
Adapter CG or CM							
R6279	6.3	0	0130-3-0230	11	8	Diode	(6)
6360	6.3	27	X352-2-9641	2	2	1.1/1.7	(1)(2)
This set up to be used on tester above serial #5000							
6360*	6.3	25	5352-2-4641	2	3	2.0/3.1	
* This set up must be used on tester below serial #5000							
6524	6.3	34	6X13-2-5600	4	3	2.4/4.5	(6) on l
			6513-2-X600	-	-	-	(6) on r
This set up must be used on testers above serial #5000							
Adapter CG or CM							
6524*	6.3	4	6513-2-5600	3	4	4.5/9.0	(6)
*This set up must be used on testers below serial #5000							
Adapter CG or CM							
(Connect two plate terminals with jumper)							
6754	6.3	12	4031-2-0809	6	8	Rect.	(1)(3)
6850	12.6	34	6X13-2-5600	4	3	2.4/4.5	(6) on l
			6513-2-X600	-	-	-	(6) on r
This set up must be used on testers above serial #5000							
Adapter CG or CM							
6850*	12.6	4	6513-2-5600	3	4	4.5/9.0	(6)
*This set up must be used on testers below serial #5000							
Adapter CG or CM							
(Connect two plate terminals with jumper)							

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
6939	6.3	17	53X1-1-4692	5	3	5.3/8.1	(1)(2)
6943	6.3	15	5317-4-2630	5	3	2.3/3.6	
7534/							
E130L	6.3	13	0106-5-0230	3	4	8.0/16.	(6)
8106	12.6	19	4361-2-3563	4	4	5.2/8.1	

THE TRIPLETT ELECTRICAL INSTRUMENT CO.

Bluffton, Ohio

Printed in U. S. A.

Part No. 84-130-061463-7



**Publication Digitized and Provided By
Steve's Antique Technology
Vintage Schematics and Publications
www.StevenJohnson.com**

Digital File Copyright © 2010 - 2020 StevenJohnson.com.

This File Provided Free At StevenJohnson.com - Not For Resale In Any Form