

Roll Chart provided free at StevenJohnson.com. Not for resale in any form.

Model 6000-6000A- 6005 Tube Testers

Code No. 3200-244

Supersedes 3200-236

STOP

FALL 1970

STOP

THE HICKOK ELECTRICAL INSTRUMENT COMPANY, CLEVELAND, OHIO, 1970

PRINTED IN U. S. A.

NEITHER THIS CHART NOR ANY PART THEREOF MAY BE COPIED WITHOUT PERMISSION OF THE COPYRIGHT OWNER.

- Note 1:** Connect lead provided to the top cap of the tube to be tested. The operating function of the cap will then be determined by the SELECTOR settings.
- Note 2:** The symbol # in the Bias column indicates Bias should be set at 100 and with Test button pressed rotate Bias dial until tube strikes.
- Note 3:** The symbol ‡ to the right of the tube type indicates that for TUBE TESTER Models 6000 and 6005, the Universal Adapter CA-5, 1050-164 is available for testing tubes with the more recent type basings, such as Compactrons, Novars, 5 and 7 pin Nuvistors and the new 10-pin tubes, including Decals. The CA-4, 1050-135 Adapter (Discontinued) can still be used but requires the use of the SA-11, 1050-177 Adapter for testing Decal types. Test data for these tubes is supplied in supplementary form with the adapters.
- Note 4:** For Models not having Subminiature Sockets Use Hickok Adapter SA-1 Code No. 1050-94

{0Z4	OFF	AP-0508-0	0	91	G	----	Plate No. 1
{0Z4	OFF	AP-0308-0	0	91	G	----	Plate No. 2
1A3	1.4	HR-0203-0	0	0	C	----	Diode
1AD2‡	1.4	B3-0X00-0	0	42	F	----	OK ABOVE DIODES OK
1AD4	1.1	DV-4120-0	17	62	B	1400	
1AG4	1.1	DV-4120-0	27	48	B	1000	
1AH4	1.1	FT-4120-0	17	0	B	500	
1AK4	1.1	FT-4120-0	17	0	B	500	
1AU2	1.1	EV-0900-0	81	----	F	----	OK ABOVE DIODES OK
1AY2	1.1	CX-0X00-0	0	86	F	----	OK ABOVE DIODES OK SET FIL. PINS ON OCTAL SOCKET PINS 2 & 7 WITH EXTERNAL LEADS
1B3	1.1	HS-0X00-0	0	80	F	----	OK ABOVE DIODES OK
1BC2	1.1	BV-0X00-0	0	73	F	----	
1BH2	1.1	DW-0X00-0	0	73	F	----	CONNECT FIL. LUGS TO OCTAL SOCKET PINS 3 & 6
1BK2	1.4	BS-0X00-0	0	85	F	----	OK ABOVE DIODES OK
1BX2	1.4	BS-0X00-0	0	80	F	----	OK ABOVE DIODES OK
1BY2‡	1.1	B3-0X00-0	0	42	F	----	OK ABOVE DIODES OK
1D-K29	1.1	BS-0X00-0	0	0	D	----	CONNECT FIL. LEADS TO PINS 1 AND 2. OK ABOVE 200 ON 3000 SCALE
1G3	1.1	HS-0X00-0	0	80	F	----	OK ABOVE DIODES OK
1H2	1.4	BS-0X00-0	0	76	F	----	OK ABOVE DIODES OK
1K3	1.1	HS-0X00-0	0	42	F	----	OK ABOVE DIODES OK

{8BN8	7.5	EV-8709-0	22	48	A	1000	Triode Sect.
{8BN8	7.5	EV-0603-0	0	78	C	----	Diode No. 1
{8BN8	7.5	EV-0102-0	0	78	C	----	Diode No. 2
{8BN11‡	10.0	53-7A98-X	10	85	A	3800	CONNECT A 2.7 OHM 3W 5% RESISTOR BETWEEN PIN 1 & 5 ON NOVAR SOCKET. PENT. NO. 1
{8BN11	10.0	93-3542-6	10	85	A	3800	CONNECT A 2.7 OHM 3W 5% RESISTOR BETWEEN PIN 1 & 9 ON NOVAR SOCKET. PENT. NO. 2
8BQ5	7.5	EV-2793-0	12	90	A	7500	
{8BQ11‡	7.5	B3-X89A-7	5	85	A	4000	Pent. No. 1
{8BQ11	7.5	B3-5236-4	5	89	A	5000	Pent. No. 2
{8BU11‡	7.5	B3-8X9A-0	10	85	A	3800	Pent. Sect.
{8BU11	7.5	B3-6705-0	15	89	A	5000	Triode No. 1
{8BU11	7.5	B3-4302-0	15	89	A	5000	Triode No. 2
{8CB11‡	7.5	B3-X89A-7	10	85	A	3700	Pent. No. 1
{8CB11	7.5	B3-5236-4	10	85	A	3700	Pent. No. 2
{8CG7	7.5	EV-7608-9	23	79	A	2600	Triode No. 1
{8CG7	7.5	EV-2103-9	23	79	A	2600	Triode No. 2
{8CM7	7.5	EV-7603-0	27	73	A	2000	Triode No. 1
{8CM7	7.5	EV-8109-0	24	87	A	4400	Triode No. 2
{8CN7	7.5	EV-7806-0	11	56	A	1200	Triode Sect.
{8CN7	7.5	EV-0203-0	0	77	C	----	Diode No. 1
{8CN7	7.5	EV-0103-0	0	77	C	----	Diode No. 2
{8CS7	7.5	EV-7608-0	22	75	A	2200	Triode No. 1
{8CS7	7.5	EV-3109-0	27	87	A	4500	Triode No. 2
{8CW5	7.5	EV-2793-0	40	89	A	5500	
{8CX8	7.5	EV-7986-0	16	83	A	3300	Pent. Sect.
{8CX8	7.5	EV-2301-0	15	81	A	2900	Triode Sect.
{8EB8	7.5	EV-7986-0	11	87	A	5100	Pent. Sect.
{8EB8	7.5	EV-2301-0	11	70	A	2000	Triode Sect.
{8EM5	7.5	EV-3917-0	12	89	A	4300	
{8ET7	7.5	EV-7986-0	10	89	A	4750	Pent. Sect.
{8ET7	7.5	EV-0301-0	0	21	C	----	Diode No. 1
{8ET7	7.5	EV-0201-0	0	21	C	----	Diode No. 2
{8FQ7	7.5	EV-7608-0	23	79	A	2600	Triode No. 1
{8FQ7	7.5	EV-2103-0	23	79	A	2600	Triode No. 2
{8GK6	7.5	EV-2781-3	10	90	A	5750	
{8GN8	7.5	EV-7986-0	10	90	A	6000	Pent. Sect.
{8GN8	7.5	EV-2301-0	16	60	A	1300	Triode Sect.

2FH5	2.5	ET-2507-0	14	87	A	4600		9MN8†	10.0	B3-8603-0	25	68	A	1850	Triode No. 1
2FQ5	2.5	ET-2507-0	19	87	A	4500		9MN8	10.0	B3-X403-0	25	68	A	1850	Triode No. 2
2FQ5A	2.5	ET-2507-0	19	89	A	5200		9MN8	10.0	B3-A203-0	25	68	A	1850	Triode No. 3
2FS5	2.5	ET-1567-0	10	85	A	3500									
2FV6	2.5	ET-1567-2	12	85	A	3800		9V9†	10.0	FW-3741-2	10	48	B	1000	HEPT. SECT. USE ADAPTER SA-11, 1050-177. MODEL 6000, 6005 NOTE 3
2GK5	2.5	ET-2507-6	20	87	A	4400									
2GU5	2.5	ET-1562-0	13	89	A	5500		9V9	10.0	FW-8X09-0	22	81	A	3000	Triode Sect.
2GW5	2.5	ET-2105-0	20	88	A	5000		10AL11†	10.0	B3-8AX9-0	14	87	A	4300	Pent. No. 1
2HA5	2.0	ET-1507-6	20	87	A	4600		10AL11	10.0	B3-3672-4	20	21	A	620	Pent. No. 2
2HK5	2.5	ET-1502-0	19	88	A	5000		10BQ5	10.0	EV-2793-0	12	90	A	7500	
2HM5	2.5	ET-1507-6	20	87	A	4600		10CW5	10.0	EV-2793-0	40	89	A	5500	
2HQ5	2.5	ET-1507-6	20	87	A	4400		10DE7	10.0	EV-7608-0	27	73	A	2000	Triode No. 1
2T4	2.5	ET-2105-0	36	88	A	5000		10DE7	10.0	EV-2109-0	54	89	A	6500	Triode No. 2
3A2	3.0	BS-0X00-0	0	85	F	-----		10DR7	10.0	EV-7608-0	17	36	A	800	Triode No. 1
3A3	3.0	HS-0X00-0	0	75	F	-----		10DR7	10.0	EV-2109-0	56	88	A	3600	Triode No. 2
3AF4	3.0	ET-2105-0	36	85	A	4000		10EG7	10.0	HY-4506-0	30	73	A	2000	Triode No. 1
3AL5	3.0	ET-0701-6	0	78	C	-----	Diode No. 1	10EG7	10.0	HY-1203-0	50	92	A	7500	Triode No. 2
3AL5	3.0	ET-0205-6	0	78	C	-----	Diode No. 2	10EM7	10.0	HY-4506-0	10	66	A	1500	Triode No. 1
3AT2†	3.0	B3-0X00-0	0	84	F	-----	OK ABOVE DIODES OK	10EM7	10.0	HY-1203-0	53	91	A	5250	Triode No. 2
3AU6	3.0	ET-1567-2	11	76	A	2300		10GF7†	10.0	EV-9801-0	19	35	A	700	TRIODE NO. 1 USE ADAPTER SA-4, 1050-144. NOTE 3
3AV6	3.0	ET-1702-5	12	58	A	1250	Triode Sect.								
3AV6	3.0	ET-0602-0	0	26	C	-----	Diode No. 1	10GF7	10.0	EV-2603-0	57	91	A	7200	Triode No. 2
3AV6	3.0	ET-0502-0	0	26	C	-----	Diode No. 2	Model 6000	A: No Adapter Required.						
3AW2†	3.0	C3-0X00-0	0	87	F	-----	OK ABOVE DIODES OK	10GK6	10.0	EV-2781-3	10	90	A	5750	
3AW3	3.0	HS-0X00-0	0	75	F	-----		10GN8	10.0	EV-7986-0	10	90	A	6000	Pent. Sect.
3B2	3.0	HS-0X00-0	0	70	F	-----		10GN8	10.0	EV-2301-0	16	60	A	1300	Triode Sect.
3B4	2.5	EV-3710-0	50	69	A	1700		10HF8	10.0	EV-7986-0	10	88	A	4800	Pent. Sect.
3BA6	3.0	ET-1567-2	11	72	A	1900		10HF8	10.0	EV-2301-0	20	69	A	1700	Triode Sect.
3BC5	3.0	ET-1562-0	11	78	A	2500		10J10†	10.0	B3-7468-5	6	27	B	700	Pent. No. 1
3BE6	3.0	ET-7562-1	0	35	B	800	AMPL. SECT. MAKE NO GAS TEST	10J10	10.0	B3-A923-0	16	88	A	4350	Pent. No. 2
3BE6	3.0	ET-1602-7	20	90	A	6500	OSC. SECT. MAKE GAS TEST	10JA8	10.0	EV-7986-0	11	89	A	5200	Tetrode Sect.
3BL2†	3.0	B3-0X00-0	0	85	F	-----	OK ABOVE DIODES OK	10JA8	10.0	EV-2301-0	22	71	A	1850	Triode Sect.
3BM2†	3.0	B3-0X00-0	0	85	F	-----	OK ABOVE DIODES OK	10JT8	10.0	EV-7986-0	12	90	A	6000	Pent. Sect.
3BN2†	3.0	B3-0X00-0	0	68	F	-----		10JT8	10.0	EV-2301-0	20	46	A	950	Triode Sect.
3BN4	3.0	ET-2501-0	19	88	A	5000		10JY8	10.0	EV-7986-0	18	86	A	4500	Pent. Sect.
3BN4A	3.0	ET-2501-0	19	86	A	3200		10JY8	10.0	EV-2301-0	18	86	A	5000	Triode Sect.
3BN6	3.0	ET-2751-6	6	27	B	700	Limiter Grid	10KR8	10.0	EV-7986-0	14	91	A	4750	Pent. Sect.
3BN6	3.0	ET-6751-2	13	0	B	500	Quadrature Grid	10KR8	10.0	EV-2301-0	17	91	B	3900	Triode Sect.
3BS2†	3.0	B3-0X00-0	0	85	F	-----	OK ABOVE DIODES OK	10KU8	10.0	EV-7986-0	14	90	A	5500	Pent. Sect.
3BT2†	3.0	C3-0X00-0	0	87	F	-----	OK ABOVE DIODES OK	10KU8	10.0	EV-0301-0	0	26	C	-----	Diode No. 1
3BU8	3.0	EV-7821-9	11	30	F	-----	Pent. No. 1	10KU8	10.0	EV-0201-0	0	26	C	-----	Diode No. 2
3BU8	3.0	EV-7321-6	11	30	F	-----	Pent. No. 2	10LB8	10.0	EV-7986-0	14	89	A	5300	Pent. Sect.
3BW2†	3.0	B3-0X00-0	0	88	F	-----	OK ABOVE DIODES OK	10LB8	10.0	EV-2301-0	17	84	A	3600	Triode Sect.
3BX6	3.0	EV-2781-9	10	86	A	4200		10LE8	10.0	EV-9683-7	10	65	A	1500	Pent. No. 1
3BY6	3.0	ET-1562-7	12	56	A	1200	Grid No. 1	10LE8	10.0	EV-9183-2	10	65	A	1500	Pent. No. 2
3BY6	3.0	ET-7562-1	16	0	B	500	Grid No. 3	10LW8	10.0	EV-7986-0	14	89	A	5000	Pent. Sect.
3BZ6	3.0	ET-1562-7	11	81	A	3000		10LW8	10.0	EV-2301-0	22	59	A	1300	Triode Sect.
3C4	2.5	BX-6230-0	41	56	A	1200		10LY8	10.0	EV-7986-0	22	85	A	3400	Pent. Sect.
3CA3	3.0	HS-0X00-0	0	83	F	-----	OK ABOVE DIODES OK	10LY8	10.0	EV-2301-0	17	48	A	1100	Triode Sect.
3CB6	3.0	ET-1562-7	11	82	A	3300		10LZ8	10.0	EV-7986-0	14	87	A	4000	Pent. Sect.
3CE5	3.0	ET-1562-0	11	81	A	3000		10LZ8	10.0	EV-2301-0	21	0	A	500	Triode Sect.
3CN3A	3.0	HS-0X00-0	0	87	F	-----	OK ABOVE DIODES OK	10T10†	10.0	B3-8AX9-0	19	88	A	4500	Pent. No. 1
3CS6	3.0	ET-1562-7	11	15	B	600	GRID NO. 1 MAKE GAS TEST	10T10	10.0	B3-3762-5	14	21	B	625	Pent. No. 2
3CS6	3.0	ET-7562-1	0	31	B	750	GRID NO. 3 MAKE NO GAS TEST	10Z10†	10.0	B3-7468-5	6	27	B	700	Pent. No. 1
3CU3	3.0	HS-0X00-0	0	85	F	-----	OK ABOVE DIODES OK	10Z10	10.0	B3-A923-0	16	88	A	4350	Pent. No. 2
3CX3	3.0	DY-0X00-0	0	87	F	-----		11AF9†	12.6	FW-8X97-0	13	88	A	5000	PENT. NO. 1. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005. NOTE 3
3CY5	3.0	ET-1562-0	11	81	B	3000									
3CZ3	3.0	HS-0X00-0	0	85	F	-----	OK ABOVE DIODES OK	11AF9	12.6	FW-1432-0	13	83	A	3300	Pent. No. 2
3DA3	3.0	DY-0X00-0	0	87	F	-----		11AR11†	10.0	B3-X89A-7	10	81	A	2700	Pent. No. 1
3DB3	3.0	HS-0X00-0	0	75	F	-----	OK ABOVE DIODES OK	11AR11	10.0	B3-5236-4	10	81	A	2700	Pent. No. 2
3DC3	3.0	HS-0X00-0	0	85	F	-----	OK ABOVE DIODES OK	11BQ11†	12.6	B3-X89A-7	10	85	A	3500	PENT. NO. 1 MAKE "LINE TEST" AT

3DA3	3.0	DY-0X00-0	0	87	F	-----		11AR11†	10.0	B3-X89A-7	10	81	A	2700	Pent. No. 1
3DB3	3.0	HS-0X00-0	0	75	F	-----	OK ABOVE DIODES OK	11AR11	10.0	B3-5236-4	10	81	A	2700	Pent. No. 2
3DC3	3.0	HS-0X00-0	0	85	F	-----	OK ABOVE DIODES OK	11BQ11†	12.6	B3-X89A-7	10	85	A	3500	Pent. No. 1 MAKE "LINE TEST" AT 1400 ON 3000 SCALE
3DF3	3.0	DY-0X00-0	0	87	F	-----									
3DG4	3.0	DR-0700-0	0	89	D	-----	Plate No. 1	11BQ11	12.6	B3-5236-4	10	87	A	4000	Pent. No. 2
3DG4	3.0	DR-0500-0	0	89	D	-----	Plate No. 2	11BT11†	10.0	B3-A2X8-6	13	89	A	6000	Pent. Sect.
3DH3	3.0	DY-0X00-0	0	88	F	-----	OK ABOVE DIODES OK	11BT11	10.0	B3-5706-0	16	77	A	2800	Triode No. 1
3DJ3	3.0	HS-0X00-0	0	88	F	-----	OK ABOVE DIODES OK	11BT11	10.0	B3-3904-0	23	78	A	3000	Triode No. 2
3DK6	3.0	ET-1562-7	12	83	A	3300		11CA11†	10.0	B3-8AX9-7	20	86	A	4250	Pent. Sect.
3DT6	3.0	ET-1562-7	23	15	A	600	Grid No. 1	11CA11	10.0	B3-6405-0	20	73	A	2350	Triode No. 1
3DT6	3.0	ET-7562-1	16	0	B	500	Grid No. 3	11CA11	10.0	B3-3207-0	20	75	A	2500	Triode No. 2
3DX4	3.0	ET-2105-0	29	85	A	3800		11CF11†	10.0	B3-5346-0	5	91	A	8000	Pent. Sect.
3DZ4	3.0	ET-2105-0	35	87	A	4000		11CF11	10.0	B3-9X08-0	5	86	A	4300	Triode No. 1
3EA5	3.0	ET-1562-0	11	86	A	4000		11CF11	10.0	B3-A207-0	5	89	A	5500	Triode No. 2
3EH7	3.0	EV-2781-9	15	87	A	3300		11CY7	10.0	EV-7608-0	10	53	A	1100	Triode No. 1
3EJ7	3.0	EV-2781-9	10	87	A	2000		11CY7	10.0	EV-2109-0	60	86	A	4000	Triode No. 2
3ER5	3.0	ET-2567-0	10	89	A	5000		11DS5	12.6	ET-1562-0	13	87	A	4800	
3EV5	3.0	ET-1562-0	21	87	A	4000		11FY7†	10.0	B3-XA09-0	20	32	A	800	Triode No. 1
3FH5	3.0	ET-2507-0	14	87	A	4600		11FY7	10.0	B3-3507-0	54	92	A	6500	Triode No. 2
3FS5	3.0	ET-1567-0	10	85	A	3500		11HM7	10.0	EV-2781-9	12	90	A	6000	
3GK5	3.0	ET-2507-6	20	87	A	4400		11JE8	10.0	EV-7986-0	11	89	A	5000	Pent. Sect.
3GW5	3.0	ET-2105-0	20	88	A	5000		11JE8	10.0	EV-2301-0	12	78	A	2200	Triode Sect.
3HA5	2.5	ET-1507-6	20	87	A	4600		11KV8	10.0	EV-7986-0	11	91	A	7400	Pent. Sect.
3HK5	3.0	ET-1502-0	19	88	A	5000		11KV8	10.0	EV-2301-0	19	72	A	1900	Triode Sect.
3HM5	3.0	ET-1507-6	20	87	A	4600		11LQ8	10.0	EV-7986-0	11	91	A	7400	Pent. Sect.
3HQ5	3.0	ET-1507-6	20	87	A	4400		11LQ8	10.0	EV-2301-0	17	90	A	6500	Triode Sect.
3JC6	3.0	EV-2781-9	11	88	A	5000		11LT8	12.6	EV-9321-6	10	80	A	3200	Pent. Sect. MAKE "LINE TEST" AT 1400 ON 3000 SCALE
3JD6	3.0	EV-2781-9	10	83	A	3200									
3KF8	3.0	EV-7821-9	10	17	A	700	Pent. No. 1	11LT8	12.6	EV-0607-0	0	81	D	-----	Diode No. 1
3KF8	3.0	EV-7321-6	10	17	A	700	Pent. No. 2	11LT8	12.6	EV-0807-0	0	81	D	-----	Diode No. 2
3KT6	3.0	EV-2781-9	15	81	A	2350									
3V4	3.0	HR-6230-0	35	68	A	1650		11Y9†	10.0	FW-8X97-0	13	88	A	5000	Pent. No. 1 USE ADAPTER SA-11, 1050-177, MODEL 6000, 6005 NOTE 3
4AU6	4.3	ET-1567-2	11	76	A	2300									
4AV6	4.3	ET-1702-5	12	58	A	1250	Triode Sect.	11Y9	10.0	FW-1432-0	13	83	A	3300	Pent. No. 2
4AV6	4.3	ET-0602-0	0	26	C	-----	Diode No. 1	12AE10†	12.6	B3-8AX9-0	23	82	A	3200	Pent. No. 1
4AV6	4.3	ET-0502-0	0	26	C	-----	Diode No. 2	12AE10	12.6	B3-3762-5	22	35	A	800	Pent. No. 2
4BC5	4.3	ET-1562-0	11	78	A	2500		12AF3	12.6	EV-020X-0	0	80	D	-----	
4BC8	4.3	EV-7608-9	16	90	A	6200	Triode No. 1	12AL5	12.6	ET-0701-6	0	78	C	-----	Diode No. 1
4BC8	4.3	EV-2103-9	16	90	A	6200	Triode No. 2	12AL5	12.6	ET-0205-6	0	78	C	-----	Diode No. 2
4BN6	4.3	ET-2751-6	6	27	B	700	Limiter Grid	12AL11†	12.6	B3-8AX9-0	14	87	A	4300	Pent. No. 1
4BN6	4.3	ET-6751-2	13	0	B	500	Quadrature Grid	12AL11†	12.6	B3-3672-4	20	21	A	620	Pent. No. 2
4BQ7A	4.3	EV-7608-9	13	90	A	6400	Triode No. 1	12AQ5	12.6	ET-1562-0	11	86	A	4100	
4BQ7A	4.3	EV-2103-9	13	90	A	6400	Triode No. 2	12AT6	12.6	ET-1702-0	10	60	A	1300	Triode Sect.
4BS8	4.3	EV-7608-9	19	87	A	4500	Triode No. 1	12AT6	12.6	ET-0602-0	0	26	C	-----	Diode No. 1
4BS8	4.3	EV-2103-9	19	87	A	4500	Triode No. 2	12AT6	12.6	ET-0502-0	0	26	C	-----	Diode No. 2
4BU8	4.3	EV-7821-9	11	30	F	-----	Pent. No. 1	12AT7	12.6	EV-7608-0	11	82	A	3000	Triode No. 1
4BU8	4.3	EV-7321-6	11	30	F	-----	Pent. No. 2	12AT7	12.6	EV-2103-0	11	82	A	3000	Triode No. 2
4BZ6	4.3	ET-1562-7	11	81	A	3000		12AU6	12.6	ET-1567-2	11	76	A	2300	
4BZ7	4.3	EV-7608-9	16	87	A	4500	Triode No. 1	12AU7	12.6	EV-7608-0	24	75	A	2200	Triode No. 1
4BZ7	4.3	EV-2103-9	16	87	A	4500	Triode No. 2	12AU7	12.6	EV-2103-0	24	75	A	2200	Triode No. 2
4CB6	4.3	ET-1562-7	11	82	A	3300		12AV5	12.6	HS-1583-0	42	89	A	5500	
4CS6	4.3	ET-1562-7	11	15	B	600	GRID NO. 1 MAKE GAS TEST	12AV6	12.6	ET-1702-5	12	58	A	1250	Triode Sect.
4CS6	4.3	ET-7562-1	0	31	B	750	GRID NO. 3 MAKE NO GAS TEST	12AV6	12.6	ET-1602-0	0	26	C	-----	Diode No. 1
4CY5	4.3	ET-1562-0	11	81	B	3000		12AV6	12.6	ET-1502-0	0	26	C	-----	Diode No. 2
4DE6	4.3	ET-1562-7	11	81	A	3000		12AX3†	12.6	B3-0407-0	0	82	D	-----	
4DK6	4.3	ET-1562-7	12	83	A	3300		12AX7	12.6	EV-7608-0	12	58	A	1250	Triode No. 1
4DT6	4.3	ET-1562-7	23	15	A	600	Grid No. 1	12AX7	12.6	EV-2103-0	12	58	A	1250	Triode No. 2
4DT6	4.3	ET-7562-1	16	0	B	500	Grid No. 3	12AY3†	12.6	EV-0209-0	0	87	D	-----	USE ADAPTER SA-4, 1050-144, NOTE 3
4EH7	4.3	EV-2781-9	15	87	A	3300		Model 6000 A:	No Adapter Required.						
4EJ7	4.3	EV-2781-9	10	87	A	2000		12AY7	12.6	EV-7608-0	18	58	A	1250	Triode No. 1
4ES8	4.3	EV-7608-0	22	92	A	7500	Triode No. 1	12AY7	12.6	EV-2103-0	18	58	A	1250	Triode No. 2
								12AZ7	12.6	EV-7608-0	11	81	A	3000	Triode No. 1

5HB7	5.0	EV-9601-0	11	83	A	4800	Triode No. 1	12W6	12.6	HS-8348-0	0	40	D	-----	Plate No. 1
5HC7†	5.0	B3-9X04-0	12	84	A	3500	Triode No. 2	12X4	12.6	ET-0607-1	0	40	D	-----	Plate No. 2
5HC7	5.0	B3-A203-0	19	27	A	700	Pent. Sect.	12X4	12.6	ET-0107-6	0	40	D	-----	USE ADAPTER SA-3, 1050-127, NOTE 3
5HG8	5.0	EV-2893-0	10	84	A	3600	Triode Sect.	13CW4†	12.6	DR-4208-0	23	79	A	2600	
5HG8	5.0	EV-6703-0	32	82	A	3200		Model 6000 A:							
5HZ6	5.0	ET-1562-7	10	65	A	1400		13CW4	12.6	13-4208-0	23	79	A	2600	
5J6	5.0	ET-5207-0	21	81	A	3000	Triode No. 1	13DE7	12.6	EV-7608-0	27	73	A	2000	Triode No. 1
5J6	5.0	ET-6107-0	21	81	A	3000	Triode No. 2	13DE7	12.6	EV-2109-0	54	89	A	6500	Triode No. 2
5JK6	5.0	ET-1562-7	10	86	A	4800		13DR7	12.6	EV-7608-0	17	36	A	800	Triode No. 1
5JL6	5.0	ET-1562-7	16	85	A	4200		13DR7	12.6	EV-2109-0	56	88	A	3600	Triode No. 2
5KD8	5.0	EV-2637-0	10	79	A	2600	Pent. Sect.	13EM7	12.6	HY-4506-0	10	66	A	1500	Triode No. 1
5KD8	5.0	EV-9108-0	19	89	A	5200	Triode Sect.	13EM7	12.6	HY-1203-0	53	91	A	5250	Triode No. 2
5KE8	5.0	EV-2637-0	11	85	A	3700	Pentode Sect.	13FD7	12.6	EV-7608-0	10	68	A	1600	Triode No. 1
5KE8	5.0	EV-9108-0	20	87	A	4500	Triode Sect.	13FD7	12.6	EV-2109-0	58	89	A	4500	Triode No. 2
5KZ8	5.0	EV-2673-0	12	82	A	3200	Pent. Sect.	13FM7†	12.6	B3-XA09-0	20	46	A	950	Triode No. 1
5KZ8	5.0	EV-9108-0	22	84	A	3600	Triode Sect.	13FM7	12.6	B3-8507-0	62	88	A	5250	Triode No. 2
5LJ8	5.0	EV-9678-0	10	80	A	2800	Pent. Sect.	13GF7†	12.6	EV-9801-0	19	35	A	700	TRIODE NO. 1 USE ADAPTER SA-4, 1050-144, NOTE 3
5LJ8	5.0	EV-1203-0	10	79	A	2600	Triode Sect.	13GF7	12.6	EV-2603-0	57	91	A	7200	Triode No. 2
5MB8	5.0	EV-9678-0	8	84	A	4000	Pent. Sect.	Model 6000 A: No Adapter Required.							
5MB8	5.0	EV-1203-0	13	88	A	4800	Triode Sect.	13J10†	12.6	B3-7468-5	6	27	B	700	Pent. No. 1
5MQ8	5.0	EV-2637-0	15	80	A	3000	Pent. Sect.	13J10	12.6	B3-A923-0	16	88	A	4350	Pent. No. 2
5MQ8	5.0	EV-9108-0	20	83	A	3300	Triode Sect.	13JZ8†	12.6	B3-7489-0	25	88	A	3900	Pent. Sect.
5R4	5.0	JS-0600-0	0	45	D	-----	Plate No. 1	13JZ8	12.6	B3-X20A-0	29	65	A	1350	Triode Sect.
5R4	5.0	JS-0400-0	0	35	D	-----	Plate No. 2	13V10†	12.6	B3-8AX9-0	21	87	A	4200	Pent. No. 1
5T8	5.0	EV-8907-0	11	56	A	1200	Triode Sect.	13V10	12.6	B3-3762-5	24	0	A	500	Pent. No. 2
5T8	5.0	EV-0607-0	0	77	C	-----	Diode No. 1	13Z10†	12.6	B3-7468-5	6	27	B	700	Pent. No. 1
5T8	5.0	EV-0203-0	0	77	C	-----	Diode No. 2	13Z10	12.6	B3-A923-0	16	88	A	4350	Pent. No. 2
5T8	5.0	EV-0107-0	0	77	C	-----	Diode No. 3	14BL11†	12.6	B3-A2X8-0	13	90	A	5500	Pent. Sect.
5U4G	5.0	JS-0600-0	0	45	D	-----	Plate No. 1	14BL11	12.6	B3-5706-0	14	82	A	3000	Triode No. 1
5U4G	5.0	JS-0400-0	0	35	D	-----	Plate No. 2	14BL11	12.6	B3-3904-0	22	82	A	3000	Triode No. 2
5U4GA,B	5.0	JS-0600-0	0	70	D	-----	Plate No. 1	14BR11†	12.6	B3-2A34-0	10	89	A	4750	Pent. Sect.
5U4GA,B	5.0	JS-0400-0	0	65	D	-----	Plate No. 2	14BR11	12.6	B3-8605-0	17	81	A	2600	Triode No. 1
5U8	5.0	EV-2637-0	11	73	A	2000	Pent. Sect.	14BR11	12.6	B3-X907-0	14	82	A	3000	Triode No. 2
5U8	5.0	EV-9108-0	12	90	A	6200	Triode Sect.	14GT8	12.6	EV-8907-0	10	15	A	600	Triode Sect.
5U9†	6.3	FW-3782-4	10	83	A	3300	PENT. SECT. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3	14GT8	12.6	EV-0601-0	0	80	C	-----	Diode No. 1
5U9	6.3	FW-X901-0	29	81	A	3000	Triode Sect.	14GT8	12.6	EV-0203-0	0	80	C	-----	Diode No. 2
5V3	6.3	JS-0600-4	0	80	D	-----	Plate No. 1	14JG8	12.6	EV-8907-0	10	65	A	1500	Triode Sect.
5V3	6.3	JS-0400-6	0	70	D	-----	Plate No. 2	14JG8	12.6	EV-0601-0	0	77	C	-----	Diode No. 1
5V4	5.0	JS-0600-0	0	85	D	-----	Plate No. 1	14JG8	12.6	EV-0203-0	0	77	C	-----	Diode No. 2
5V4	5.0	JS-0400-0	0	85	D	-----	Plate No. 2	15AF11†	17.0	B3-A2X9-0	8	90	A	5400	PENT. SECT. MAKE "LINE TEST" AT 1450 ON 3000 SCALE
5V6	5.0	HS-5348-0	13	86	A	4100		15AF11	17.0	B3-6805-0	17	81	A	2700	Triode No. 1
5V9†	5.0	FW-3741-2	10	48	B	1000	HEPT. SECT. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3	15AF11	17.0	B3-3407-0	13	82	A	2800	Triode No. 2
5V9	5.0	FW-8X09-0	22	81	A	3000	Triode Sect.	15BD11†	17.0	B3-A2X9-0	12	87	A	4500	PENT. SECT. MAKE "LINE TEST" AT 1400 ON 3000 SCALE
5X8	5.0	EV-7986-1	12	81	A	3000	Pent. Sect.	15BD11	17.0	B3-6805-0	13	78	A	2500	Triode No. 1
5X8	5.0	EV-2306-1	20	84	A	3500	Triode Sect.	15BD11	17.0	B3-3407-0	10	80	A	2750	Triode No. 2
5X9†	6.3	FW-3782-4	10	84	A	3600	PENT. SECT. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3	15CW5	17.0	EV-2793-0	42	88	A	5000	MAKE "LINE TEST" AT 1400 ON 3000 SCALE.
5X9	6.3	FW-X901-0	12	81	A	3000	Triode Sect.	15EW7	17.0	EV-7608-0	30	63	A	1450	TRIODE NO. 1 MAKE "LINE TEST" AT 1400 ON 3000 SCALE
5Y3	5.0	JS-0600-0	0	22	D	-----	Plate No. 1	15EW7	17.0	EV-2109-0	56	91	A	4350	Triode No. 2
5Y3	5.0	JS-0400-0	0	18	D	-----	Plate No. 2	15FM7†	12.6	B3-XA09-0	20	46	A	950	Triode No. 1
6AB4	6.3	ET-6107-0	10	85	A	4000		15FM7	12.6	B3-8507-0	59	88	A	5250	Triode No. 2
6AB9†	6.3	FW-978X-0	15	81	A	3000	TETRODE NO. 1. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3	15FY7†	17.0	B3-XA09-0	18	33	A	750	TRIODE NO. 1 MAKE "LINE TEST" AT 1450 ON 3000 SCALE
6AB9	6.3	FW-3124-0	15	81	A	3000	Tetrode No. 2	15FY7	17.0	B3-3507-0	47	91	A	6500	Triode No. 2
6AC7	6.3	HS-4865-3	11	81	A	3000		15HA6	17.0	EV-2761-3	10	90	A	6500	
6AC9†	6.3	B3-9AX8-7	10	87	A	4200	Pent. Sect.	15HB6	17.0	EV-2781-9	20	88	A	5000	
6AC9	6.3	B3-0304-0	0	85	C	-----	Diode No. 1								
6AC9	6.3	B3-0203-0	0	85	C	-----	Diode No. 2								
6AC10†	6.3	B3-0Y04-0	14	85	A	3700	Triode No. 1	15KY8†	17.0	EV-2673-0	42	80	A	2550	PENT. SECT. MAKE "LINE TEST" AT 1425 ON 3000 SCALE

6AB9	6.3	FW-3124-0	15	81	A	3000	Tetrode No. 2
6AC7	6.3	HS-4865-3	11	81	A	3000	
6AC9†	6.3	B3-9AX8-7	10	87	A	4200	Pent. Sect.
6AC9	6.3	B3-0304-0	0	85	C	-----	Diode No. 1
6AC9	6.3	B3-0203-0	0	85	C	-----	Diode No. 2
6AC10†	6.3	B3-9X04-0	14	85	A	3700	Triode No. 1
6AC10	6.3	B3-7506-0	14	85	A	3700	Triode No. 2
6AC10	6.3	B3-A203-0	14	85	A	3700	Triode No. 3
6AD10†	6.3	B3-3762-5	17	62	A	1900	Pent. No. 1
6AD10	6.3	B3-8AX9-0	7	89	A	3800	Pent. No. 2
6AF3	6.3	EV-020X-0	0	86	D	-----	
6AF4	6.3	ET-2105-0	36	85	A	4000	
6AF9†	6.3	FW-8X97-0	13	88	A	5000	
6AF9	6.3	FW-1432-0	13	83	A	3300	
6AF11†	6.3	B3-A2X9-0	10	88	A	4900	Pent. No. 2
6AF11	6.3	B3-6805-0	18	77	A	2400	Pent. Sect.
6AF11	6.3	B3-3407-0	10	80	A	2800	Triode No. 1
6AG5	6.3	ET-1562-0	11	78	A	2500	Triode No. 2
6AG7	6.3	HS-4865-1	11	88	A	5000	
6AG9†	6.3	B3-A2X9-4	19	78	A	2500	Pent. Sect.
6AG9	6.3	B3-5706-0	14	87	A	4600	Triode Sect.
6AG11†	6.3	B3-8709-0	16	86	A	4000	Triode No. 1
6AG11	6.3	B3-5604-0	16	86	A	4000	Triode No. 2
6AG11	6.3	B3-0X0A-0	0	80	C	-----	Diode No. 1
6AG11	6.3	B3-0302-0	0	80	C	-----	Diode No. 2
6AH9†	6.3	B3-5A87-9	10	87	A	5200	Pentode Sect.
6AH9	6.3	B3-2304-0	27	77	A	2350	Triode Sect.
6AK5	6.3	ET-1562-0	24	65	A	1500	
6AK6	6.3	ET-1567-2	20	74	A	2100	
6AK9†	6.3	B3-8597-0	30	85	A	4150	Pent. Sect.
6AK9	6.3	B3-XA07-0	18	75	A	2400	Triode No. 1
6AK9	6.3	B3-3207-0	26	59	A	1750	Triode No. 2
6AK10†	6.3	B3-9X04-0	14	85	A	4500	Triode No. 1
6AK10	6.3	B3-7506-0	14	85	A	4500	Triode No. 2
6AK10	6.3	B3-A203-0	14	85	A	4500	Triode No. 3
6AL5	6.3	ET-0701-6	0	78	C	-----	Diode No. 1
6AL5	6.3	ET-0205-6	0	78	C	-----	Diode No. 2
6AL9†	6.3	B3-A2X9-4	5	91	A	9000	Pent. Sect.
6AL9	6.3	B3-5706-0	9	88	A	6300	Triode Sect.
6AL11†	6.3	B3-8AX9-0	14	87	A	4300	Pent. No. 1
6AL11	6.3	B3-3672-4	20	21	A	620	Pent. No. 2
6AM8	6.3	EV-2631-9	11	79	A	2700	Pent. Sect.
6AM8	6.3	EV-0807-0	0	78	C	-----	Diode Sect.
6AN4	6.3	ET-2105-0	13	89	A	5500	
6AN5	6.3	ET-1567-0	13	85	B	4000	
6AN8	6.3	EV-8679-1	11	81	A	3000	Pent. Sect.
6AN8	6.3	EV-2173-6	24	83	A	3300	Triode Sect.
6AQ5	6.3	ET-1562-0	11	86	A	4100	
6AR11†	6.3	B3-X89A-7	10	81	A	2700	Pent. No. 1
6AR11	6.3	B3-5236-4	10	81	A	2700	Pent. No. 2
6AS6	6.3	ET-1562-7	11	48	B	1000	
6AS7	7.5	HY-4506-2	100	79	A	2600	Triode No. 1
6AS7	7.5	HY-1203-5	100	79	A	2600	Triode No. 2
6AS8	6.3	EV-2913-7	11	81	A	3000	Pent. Sect.
6AS8	6.3	EV-0608-0	0	78	C	-----	Diode Sect.
6AS11†	6.3	B3-A2X9-0	10	88	A	5000	Pent. Sect.
6AS11	6.3	B3-6805-0	14	85	A	3800	Triode No. 1
6AS11	6.3	B3-3407-0	16	83	A	3300	Triode No. 2
6AT6	6.3	ET-1702-0	10	60	A	1300	Triode Sect.

PENT. NO. 1. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3

15FY7†	17.0	B3-XA09-0	18	33	A	750	
15FY7	17.0	B3-3507-0	47	91	A	6500	Triode No. 2
15HA6	17.0	EV-2761-3	10	90	A	6500	
15HB6	17.0	EV-2781-9	20	88	A	5000	
15KY8†	17.0	EV-2673-0	42	80	A	2550	
15KY8	17.0	EV-9801-0	19	27	A	700	
Model 6000 A:	No Adapter Required.						
15LE8	12.6	EV-9683-7	10	57	A	1300	
15LE8	12.6	EV-9183-2	10	57	A	1300	
15MF8†	12.6	B3-7489-0	30	84	A	4000	
15MF8	12.6	B3-X20A-0	23	66	A	1900	
16AK9†	17.0	B3-8597-0	30	85	A	4150	
16AK9	17.0	B3-XA07-0	18	75	A	2400	
16AK9	17.0	B3-3207-0	26	59	A	1750	
16BQ11†	17.0	B3-X89A-7	10	85	A	3500	
16BQ11	17.0	B3-5236-4	10	87	A	4000	
16BX11†	17.0	B3-2A3X-0	5	88	A	4900	
16BX11	17.0	B3-8709-0	5	89	A	5500	
16BX11	17.0	B3-5604-0	5	90	A	6000	
16GK6	17.0	EV-2781-3	7	90	A	5900	
16GY5†	17.0	B3-527X-0	30	92	B	9000	
16HB5†	17.0	B3-A72X-0	57	89	A	5600	
16JV6†	17.0	B3-A732-X	55	91	A	7000	
16KA6†	17.0	B3-523X-4	57	89	A	5500	
16LU8†	17.0	B3-6489-0	40	87	A	4000	
16LU8	17.0	B3-X20A-0	24	62	A	1400	
16Y9†	17.0	FW-8X97-0	13	88	A	5000	
16Y9	17.0	FW-1432-0	13	83	A	3300	
17AB9†	17.0	FW-978X-0	15	81	A	3000	
17AB9	17.0	FW-3124-0	15	81	A	3000	
17AB10†	17.0	B3-7468-5	6	27	B	700	
17AB10	17.0	B3-5468-7	13	0	B	500	
17AB10	17.0	B3-A923-0	25	83	A	3100	
17AX3†	17.0	B3-0407-0	0	82	D	-----	
17AX4	17.0	HY-0503-0	0	82	D	-----	
17AY3†	17.0	EV-0209-0	0	87	D	-----	
Model 6000 A:	No Adapter Required.						
17BE3†	17.0	B3-0X07-0	0	89	D	-----	
17BF11†	17.0	B3-8AX9-0	25	88	A	5000	
17BF11	17.0	B3-3762-5	13	7	A	540	
17BH3†	17.0	EV-0209-0	0	87	D	-----	
Model 6000 A:	No Adapter Required.						
17BQ6	17.0	HS-5X48-0	42	89	A	5500	
17BS3†	17.0	EV-0209-0	0	83	D	-----	
Model 6000 A:	No Adapter Required.						
17BW3†	17.0	B3-0407-0	0	89	D	-----	
17BZ3†	17.0	B3-0X07-0	0	86	C	-----	
17C5	17.0	ET-2761-0	20	91	B	7500	
17C9†	17.0	EV-7986-0	15	85	A	3200	
17C9	17.0	EV-132X-0	15	85	A	3200	
17CK3†	17.0	EV-0209-0	0	86	C	-----	
Model 6000 A:	No Adapter Required.						

PENT. SECT. MAKE "LINE TEST" AT 1425 ON 3000 SCALE USE ADAPTER SA-4, 1050-144. NOTE 3

PENT. NO. 1. MAKE "LINE TEST" AT 1425 ON 3000 SCALE

PENT. SECT. MAKE "LINE TEST" AT 1450 ON 3000 SCALE

DO NOT USE TESTER CAP CONNECTOR. CONNECT CAP TO PIN 2 OF OCTAL SOCKET

DO NOT USE TESTER CAP CONNECTOR. CONNECT CAP TO PIN 2 OF N OCTAL SOCKET

PENT. NO. 1. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3

TETRODE NO. 1. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3

USE ADAPTER SA-4, 1050-144. NOTE 3

USE ADAPTER SA-4, 1050-144. NOTE 3

OK ABOVE DIODES OK

Tetrode No. 1

Tetrode No. 2 USE ADAPTER SA-4, 1050-144. NOTE 3

Part No.	Part Name	Value	Code	Notes	Part No.	Value	Code	Notes
6BD11	B3-6805-0	17	78	A 2500	18FY6	17.0	ET-1702-0	21 0
6BD11	B3-3407-0	11	80	A 2750	18FY6	17.0	ET-0602-0	0 32
6BE3†	B3-0X07-0	0	89	D -----	18GD6A	17.0	ET-0502-0	0 32
6BE6	ET-7562-1	0	35	B 800	19AQ5	20.0	ET-1567-2	15 73
6BE6	ET-1602-7	20	90	A 6500	19AU4	20.0	ET-1562-0	11 86
6BF11†	B3-8AX9-0	25	88	A 5000	19CG3†	20.0	HY-0503-0	0 89
6BF11	B3-3762-5	13	7	A 550	19CL8A	20.0	B3-0407-0	0 91
6BH3†	EV-0209-0	0	87	D -----	19CL8A	20.0	EV-9678-0	10 84
Model 6000 A:	No Adapter Required.			-----	19DE3†	20.0	EV-1203-0	12 89
6BH6	ET-1562-7	12	73	A 2000	19EA8	20.0	B3-0403-0	0 86
6BH8	EV-7986-0	7	88	A 5000	19EA8	20.0	EV-2637-0	17 79
6BH8	EV-2301-0	27	83	A 3300	19EZ8	20.0	EV-9108-0	13 89
6BH11†	B3-8X9A-0	10	84	A 3500	19EZ8	20.0	EV-9800-0	19 69
6BH11	B3-6705-0	18	89	A 5100	19EZ8	20.0	EV-7600-0	19 69
6BH11	B3-4302-0	18	89	A 5100	19EZ8	20.0	EV-2301-0	20 71
6BJ3†	B3-0X07-0	0	88	D -----	If no reading is obtained, use selector setting FU- in place of EV-.			
6BJ7	EV-0809-3	0	80	C -----	19FX5	20.0	ET-2761-0	10 90
6BJ7	EV-0607-3	0	80	C -----	19GQ7	20.0	EV-0809-0	0 80
6BJ7	EV-0201-3	0	80	C -----	19GQ7	20.0	EV-0607-0	0 80
6BJ8	EV-8709-0	27	80	A 2800	19GQ7	20.0	EV-0201-0	0 80
6BJ8	EV-0603-0	0	78	C -----	19HR6	20.0	ET-1567-2	10 84
6BJ8	EV-0102-0	0	78	C -----	19HS6	20.0	ET-1567-2	14 82
6BK4	HS-0501-X	0	45	C -----	19HV8	20.0	EV-9678-0	11 81
6BK7	EV-7608-9	20	85	A 4000	19HV8	20.0	EV-1203-0	14 59
6BK7	EV-2103-9	20	85	A 4000	19JN8	20.0	EV-9678-0	10 82
6BK11†	B3-9X04-0	20	39	A 850	19JN8	20.0	EV-1203-0	17 89
6BK11	B3-7506-0	19	7	A 550	19KG8	20.0	EV-9678-0	11 82
6BK11	B3-A203-0	19	7	A 550	19KG8	20.0	EV-2103-0	18 88
6BL7	HY-4506-0	24	88	A 5000	19Q9†	20.0	EV-132X-6	10 82
6BL7	HY-1203-0	24	88	A 5000	19Q9	20.0	EV-8907-6	18 87
6BM8	EV-3672-0	24	86	A 4300	19X8	20.0	EV-7986-1	12 81
6BM8	EV-1908-0	11	71	A 1900	19X8	20.0	EV-2306-1	20 84
6BN4	ET-2501-0	19	88	A 5000	20EW7	20.0	EV-7608-0	27 72
6BN4A	ET-2501-0	19	86	A 3200	20EW7	20.0	EV-2109-0	54 88
6BN6	ET-2751-6	6	27	B 700	20EZ7	20.0	CR-8709-0	12 58
6BN6	ET-6751-2	13	0	B 500	20EZ7	20.0	CR-5604-0	12 58
6BN8	EV-8709-0	22	48	A 1000	20LF6†	20.0	B3-5632-4	69 85
6BN8	EV-0603-0	0	78	C -----	21GY5†	20.0	B3-527X-0	30 92
6BN8	EV-0102-0	0	78	C -----	21HB5†	20.0	B3-A72X-0	57 89
6BN11†	B3-7A98-X	10	85	A 3800	21HD5†	20.0	B3-A79X-0	54 89
6BN11	B3-3542-6	10	85	A 3800	21HJ5†	20.0	B3-A792-X	54 90
6BQ5	EV-2793-0	12	90	A 7500	21JV6†	20.0	B3-A732-X	55 91
6BQ6	HS-5X48-0	42	89	A 5500	21JZ6†	20.0	B3-5632-4	56 91
6BQ7A	EV-7608-9	13	90	A 6400	21KA6†	20.0	B3-523X-4	57 89
6BQ7A	EV-2103-9	13	90	A 6400	21LG6†	20.0	B3-58A4-X	64 86
6BR8	EV-9678-0	11	73	A 2000	21LR8†	20.0	EV-2673-0	40 87
6BR8	EV-1203-0	12	90	A 6200	21LR8	20.0	EV-9801-0	24 62
6BS3†	EV-0209-0	0	83	D -----	Model 6000 A:	No Adapter Required.		
Model 6000 A:	No Adapter Required.			-----	21LU8†	20.0	B3-6489-0	40 87
6BU8	EV-7821-9	11	30	F -----	21LU8	20.0	B3-X20A-0	24 62
6BU8	EV-7321-6	11	30	F -----	22BH3†	20.0	EV-0209-0	0 87
6BV11†	B3-7X98-A	10	73	A 2000	Model 6000 A:	No Adapter Required.		
6BV11	B3-6345-2	10	73	A 2000	22BW3†	25.0	B3-0X07-0	0 89
6BW3†	B3-0407-0	0	89	D -----	22DE4	25.0	HY-2500-0	0 89
6BW8	EV-6987-0	11	73	A 2000	OK ABOVE DIODES OK			
6BW8	EV-0302-0	0	77	C -----	22BW3†	25.0	B3-0X07-0	0 89
6BW8	EV-0102-0	0	77	C -----	22DE4	25.0	HY-2500-0	0 89
6BW11†	B3-A89X-7	7	85	A 4250	Model 6000 A: No Adapter Required.			
6BW11	B3-3542-6	10	82	A 3300	22BW3†	25.0	B3-0X07-0	0 89
6BY6	ET-1562-7	12	56	A 1200	22DE4	25.0	HY-2500-0	0 89
6BY6	ET-7562-1	16	0	B 500	Model 6000 A: No Adapter Required.			

Tetrode Sect.
Triode Sect.
CONNECT JUMPER FROM TUBE CAP TO PIN 3 ON OCTAL SOCKET

Diode No. 1
Diode No. 2
Diode No. 3

Pent. Sect.
Triode Sect.
Triode No. 1
Triode No. 2
Triode No. 3

Diode No. 1
Diode No. 2
Diode No. 3

Pent. Sect.
Triode Sect.
Pent. Sect.
Triode Sect.
Pent. Sect.
Triode Sect.

CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET
DO NOT USE TESTER CAP CONNECTOR. CONNECT CAP TO PIN 2 OF OCTAL SOCKET

CONNECT A JUMPER FROM CAP TO PIN 6 OF OCTAL SOCKET
DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 2 OF THE OCTAL SOCKET

CAP-P. CONNECT CAP OF TUBE TO PIN 6 OF OCTAL SOCKET
PENT. SECT.
USE ADAPTER SA-4, 1050-144, NOTE 3

Pent. Sect.
Triode Sect.
MAKE "LINE TEST" AT 1800 ON 3000 SCALE
USE ADAPTER SA-4, 1050-144, NOTE 3

6BW3†	6.3	B3-0407-0	0	89	D	2000	OK ABOVE DIODES OK
6BW8	6.3	EV-6987-0	11	73	A	2000	Pent. Sect.
6BW8	6.3	EV-0302-0	0	77	C	-----	Diode No. 1
6BW8	6.3	EV-0102-0	0	77	C	-----	Diode No. 2
6BW11†	6.3	B3-A89X-7	7	85	A	4250	Pentode No. 1
6BW11	6.3	B3-3542-6	10	82	A	3300	Pentode No. 2
6BY6	6.3	ET-1562-7	12	56	A	1200	Grid No. 1
6BY6	6.3	ET-7562-1	16	0	B	500	Grid No. 3
6BY8	6.3	EV-1789-2	11	76	A	2300	Pent. Sect.
6BY8	6.3	EV-0603-0	0	78	C	-----	Diode Sect.
6BY11†	6.3	B3-8AX9-0	45	83	A	3800	Pent. No. 1
6BY11	6.3	B3-3762-5	15	40	A	1000	Pent. No. 2
6BZ6	6.3	ET-1562-7	11	81	A	3000	
6BZ3†	6.3	B3-0X07-0	0	86	C	-----	
6BZ7	6.3	EV-7608-9	16	87	A	4500	Triode No. 1
6BZ7	6.3	EV-2103-9	16	87	A	4500	Triode No. 2
6C4	6.3	ET-6107-0	25	75	A	2200	
6C9†	6.3	EV-7986-0	15	85	A	3200	Tetrode No. 1
6C9	6.3	EV-132X-0	15	85	A	3200	Tetrode No. 2
6C10†	6.3	B3-9X04-0	12	58	A	1250	Triode No. 1
6C10	6.3	B3-7506-0	12	58	A	1250	Triode No. 2
6C10	6.3	B3-A203-0	12	58	A	1250	Triode No. 3
6CA4	6.3	EV-0703-0	0	62	D	-----	Plate No. 1
6CA4	6.3	EV-0103-0	0	62	D	-----	Plate No. 2
6CA5	6.3	DU-2761-0	20	89	A	5500	

Model 6000 A:	No Adapter Required.						
21LU8†	20.0	B3-6489-0	40	87	A	4000	Pent. Sect.
21LU8	20.0	B3-X20A-0	24	62	A	1400	Triode Sect.
22BH3†	20.0	EV-0209-0	0	87	D	-----	MAKE "LINE TEST" AT 1800 ON 3000 SCALE USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
22BW3†	25.0	B3-0X07-0	0	89	D	-----	
22DE4	25.0	HY-0503-0	0	89	D	-----	
22JF6†	20.0	EV-2X73-8	32	92	B	7800	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
22JG6†	20.0	EV-2973-6	32	92	B	7800	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
22JR6†	20.0	EV-2913-6	65	85	A	4200	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A:	No adapter required.						
22JU6†	20.0	EV-2X73-8	72	85	A	4200	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
22KM6†	20.0	EV-2X73-8	65	89	A	5000	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
22KV6†	20.0	EV-2973-6	41	87	B	4800	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A:	No Adapter Required.						
23Z9†	25.0	B3-8597-0	35	88	A	5000	Pent. Sect.
23Z9	25.0	B3-XA07-0	20	76	A	2200	Triode No. 1
23Z9	25.0	B3-3207-0	30	69	A	1800	Triode No. 2
24BF11†	25.0	B3-8AX9-0	25	88	A	5000	Pentode No. 1
24BF11	25.0	B3-3762-5	19	7	A	600	Pentode No. 2

**KEEP YOUR TUBE TESTER UP TO DATE WITH
SAVE 60%—**

**A 2-YEAR ROLL CHART SUBSCRIPTION—
SUBSCRIBE TODAY!**

6CA7	6.3	HS-5348-1	23	90	A	6000	
6CA11†	6.3	B3-8AX9-7	20	86	A	4250	Pent. Sect.
6CA11	6.3	B3-6405-0	20	73	A	2350	Triode No. 1
6CA11	6.3	B3-3207-0	20	75	A	2500	Triode No. 2
6CB5	7.5	HS-4X13-0	40	92	A	7000	
6CB6	6.3	ET-1562-7	11	82	A	3300	
6CD3†	6.3	B3-0X07-0	0	93	D	-----	
6CD6	6.3	HS-5X83-0	35	90	A	6500	
6CE3†	6.3	B3-0407-0	0	86	C	-----	
6CE5	6.3	ET-1562-0	11	81	A	3000	
6CG3†	6.3	B3-0407-0	0	91	D	-----	
6CG7	6.3	EV-7608-9	23	79	A	2600	Triode No. 1
6CG7	6.3	EV-2103-9	23	79	A	2600	Triode No. 2
6CG8	6.3	EV-9678-0	12	81	A	3000	Pent. Sect.
6CG8	6.3	EV-1203-0	20	84	A	3500	Triode Sect.
6CH3†	6.3	EV-0209-0	0	91	D	-----	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
6CJ3†	6.3	EV-0209-0	0	86	C	-----	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
6CK3†	6.3	EV-0209-0	0	86	C	-----	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
6CL3†	6.3	EV-0209-0	0	86	C	-----	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
6CL5	6.3	HS-4X13-0	55	89	A	6500	
6CL6	6.3	EV-2631-7	11	88	A	5000	
6CL8	6.3	EV-9678-0	10	84	A	3500	Tetrode Sect.
6CL8	6.3	EV-1203-0	12	89	A	6000	Triode Sect.
6CM3†	6.3	EV-0279-0	0	90	D	-----	PLATE TO SCREEN SHORT NORMAL USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
6CM6	6.3	EV-2917-0	11	86	A	4100	

24GA7†	25.0	B3-4735-0	58	89	A	4500	Pent. Sect.
24GA7	25.0	B3-0A08-0	0	85	D	-----	Diode Sect.
24JE6A†	25.0	EV-2X73-8	39	92	B	8100	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
24JZ8†	25.0	B3-7489-0	32	86	A	4150	Pent. Sect.
24JZ8	25.0	B3-X20A-0	29	60	A	1500	Triode Sect.
24LQ6†	25.0	EV-2X73-8	39	92	B	8100	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A:	No Adapter Required.						
25AV5	25.0	HS-1583-0	42	89	A	5500	
25AX4	25.0	HY-0503-0	0	82	D	-----	
25BK5	25.0	EV-3186-0	11	88	A	5000	
25BQ6	25.0	HS-5X48-0	42	89	A	5500	
25C5	25.0	ET-2761-0	20	91	B	7500	
25CA5	25.0	DU-2761-0	20	89	A	5500	
25CD6	25.0	HS-5X83-0	35	90	A	6500	
25CG3†	25.0	B3-0407-0	0	91	D	-----	
25CK3†	25.0	EV-0209-0	0	86	C	-----	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A:	No Adapter Required.						
25CM3†	25.0	EV-0279-0	0	90	D	-----	PLATE TO SCREEN SHORT NORMAL USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
25CT3	25.0	EV-0209-0	0	94	D	-----	OK ABOVE DIODES OK
25DN6	25.0	HS-5X83-0	28	93	B	9000	
25EC6	25.0	HS-5X83-0	42	89	A	5500	
25EH5	25.0	ET-2761-0	13	88	A	10000	
25F5	25.0	ET-2761-0	25	85	A	4000	
25F5A	25.0	ET-2763-0	25	86	A	4400	
25H-B25	25.0	EV-2X79-8	50	87	A	4400	USE ADAPTER SA-8, 1050-168
25HX5	25.0	EV-7963-0	50	88	A	5000	USE ADAPTER SA-8, 1050-168
25LQ6	25.0	EV-2917-0	11	86	A	4100	

Roll Chart provided free at StevenJohnson.com. Not for resale in any form.

Part No.	Part Name	Grid	Beam Angle	Beam Current	Beam Power	Notes
6CL8	EV-9678-0	6.3	12	89	A 6000	Tetrode Sect.
{6CM3†	EV-0279-0	6.3	0	90	D	PLATE TO SCREEN SHORT NORMAL USE ADAPTER SA-4, 1050-144. NOTE 3
{Model 6000 A:	No Adapter Required.					
6CM6	EV-3917-0	6.3	11	86	A 4100	
{6CM7	EV-7603-0	6.3	27	73	A 2000	Triode No. 1
{6CM7	EV-8109-0	6.3	24	87	A 4400	Triode No. 2
{6CN7	EV-7806-0	6.3	11	56	A 1200	Triode Sect.
{6CN7	EV-0203-0	6.3	0	77	C	Diode No. 1
{6CN7	EV-0103-0	6.3	0	77	C	Diode No. 2
6CQ4	HY-0503-0	6.3	0	89	D	
{6CQ8	EV-2637-0	6.3	10	79	A 2600	Tetrode Sect.
{6CQ8	EV-9108-0	6.3	11	87	A 4300	Triode Sect.
{6CS6	ET-1562-7	6.3	11	15	B 600	GRID NO. 1 MAKE GAS TEST
{6CS6	ET-7562-1	6.3	0	31	B 750	GRID NO. 3 MAKE NO GAS TEST
{6CS7	EV-7608-0	6.3	22	75	A 2200	Triode No. 1
{6CS7	EV-3109-0	6.3	27	87	A 4500	Triode No. 2
6CT3	EV-0209-0	6.3	0	94	D	OK ABOVE DIODES OK
6CU5	ET-2761-0	6.3	11	91	B 7000	
{6CU8	EV-7236-1	6.3	11	81	A 3000	Pent. Sect.
{6CU8	EV-8901-0	6.3	24	83	A 3300	Triode Sect.
{6CW4†	DR-4208-0	6.3	23	79	A 2600	USE ADAPTER SA-3, 1050-127. NOTE 3
{Model 6000 A:						
6CW4	13-4208-0	6.3	23	79	A 2600	
6CW5	EV-2793-0	6.3	40	89	A 5500	
{6CX8	EV-7986-0	6.3	16	83	A 3300	Pent. Sect.
{6CX8	EV-2301-0	6.3	15	81	A 2900	Triode Sect.
6CY5	ET-1562-0	6.3	11	81	B 3000	
{6CY7	EV-7608-0	6.3	10	53	A 1100	Triode No. 1
{6CY7	EV-2109-0	6.3	60	86	A 4000	Triode No. 2
6CZ5	EV-3917-0	6.3	10	87	A 4500	
{6D10†	B3-9X04-0	6.3	18	78	A 2500	Triode No. 1
{6D10	B3-7506-0	6.3	18	78	A 2500	Triode No. 2
{6D10	B3-A203-0	6.3	18	78	A 2500	Triode No. 3
6DA4	HY-0503-0	6.3	0	86	D	
{6DA5	EV-19X2-0	6.3	Vary 100		F	Connect a 1 megohm resistor from cap lead to Octal Test Socket Pin No. 7. Vary Bias to vary beam angle.
6DB5	EV-3912-0	6.3	11	91	B 7500	
6DC6	ET-1562-7	6.3	10	84	A 3500	
6DE4	HY-0503-0	6.3	0	89	D	
6DE6	ET-1562-7	6.3	11	81	A 3000	
{6DE7	EV-7608-0	6.3	27	73	A 2000	Triode No. 1
{6DE7	EV-2109-0	6.3	54	89	A 6500	Triode No. 2
6DG6	HS-5348-0	6.3	11	91	B 7500	
{6DJ8	EV-7608-0	6.3	22	91	A 7000	Triode No. 1
{6DJ8	EV-2103-0	6.3	22	91	A 7000	Triode No. 2
6DK6	ET-1562-7	6.3	12	83	A 3300	
6DM4	HY-0503-0	6.3	0	89	D	
{6DN7	HY-4506-0	6.3	24	73	A 2000	Triode No. 1
{6DN7	HY-1203-0	6.3	20	91	A 7500	Triode No. 2
6DQ4	JX-0503-0	6.3	0	86	D	
6DQ5	HS-1X43-0	6.3	43	92	A 7800	
6DQ6	HS-5X48-0	6.3	25	90	B 6000	
6DR4	ET-6507-0	6.3	12	58	A 1250	
{6DR7	EV-7608-0	6.3	17	36	A 800	Triode No. 1
{6DR7	EV-2109-0	6.3	56	88	A 3600	Triode No. 2
{6DS4†	DR-4208-0	6.3	22	79	A 2600	USE ADAPTER SA-3, 1050-127. NOTE 3
{Model 6000 A:						
6DS4	13-4208-0	6.3	22	79	A 2600	
25F5A	25.0	ET-2763-0	25	86	A 4400	
25H-B25	25.0	EV-2X79-8	50	87	A 4400	
25HX5	25.0	EV-7963-0	50	88	A 5000	
{25JQ6	25.0	EV-7139-6	50	85	A 3800	
{25JQ6	25.0	EV-0609-0	0	70	C	
{25JZ8†	25.0	B3-7489-0	32	86	A 4150	
{25JZ8	25.0	B3-X20A-0	29	60	A 1500	
25L6	25.0	HS-5348-1	33	88	A 5200	
25W4	25.0	HY-0503-0	0	88	D	
26DQ5	25.0	HS-1X43-0	43	92	A 7800	
26HU5	25.0	HY-1X32-0	70	90	A 7500	
26LX6†	25.0	B3-5632-4	70	90	A 7500	
27LF6†	25.0	B3-5632-4	69	85	A 4350	
{28D7	25.0	JR-7536-2	13	83	B 3400	
{28D7	25.0	JR-2436-7	13	83	B 3400	
28HA6	25.0	EV-2761-3	10	90	A 6500	
28HD5†	25.0	B3-A79X-0	54	89	A 6000	
29GK6	25.0	EV-2781-3	10	90	A 5750	
{30AG11†	35.0	B3-8709-0	15	87	A 4000	
{30AG11	35.0	B3-5604-0	15	87	A 4000	
{30AG11	35.0	B3-0X0A-0	0	76	C	
{30AG11	35.0	B3-0302-0	0	76	C	
30HJ5†	25.0	B3-A792-X	54	90	A 6500	
30JZ6†	25.0	B3-5632-4	56	91	A 7000	
30KD6†	35.0	B3-5632-4	70	90	A 6400	
{31AL10†	35.0	B3-8457-0	26	90	A 7100	
{31AL10	35.0	B3-A90X-0	7	85	A 4000	
{31AL10	35.0	B3-3207-0	22	78	A 2900	
31JS6A†	35.0	B3-5632-4	53	88	A 4300	
{31LQ6†	35.0	EV-2X73-8	39	92	B 8100	
{Model 6000A:	No Adapter Required.					
32ET5	35.0	ET-2761-0	37	86	A 4000	
{32GA7†	35.0	B3-4735-0	58	89	A 4500	
{32GA7	35.0	B3-0A08-0	0	85	D	
{32HQ7†	35.0	B3-95A8-0	43	86	B 4500	
{32HQ7	35.0	B3-0204-0	0	84	C	
{33GT7†	35.0	B3-A5X8-0	31	91	B 6000	
{33GT7	35.0	B3-0204-0	0	95	D	
{33GY7†	35.0	B3-X5A8-0	31	91	B 6000	
{33GY7	35.0	B3-0204-0	0	95	D	
{33HE7†	35.0	B3-95A8-0	54	91	A 7000	
{33HE7	35.0	B3-0204-0	0	89	D	
{33JR6†	35.0	EV-2913-6	65	85	A 4200	
{Model 6000 A:	No Adapter Required.					
33JV6†	35.0	B3-A732-X	55	91	A 7000	
34CD3†	35.0	B3-0X07-0	0	93	D	
34CE3†	35.0	B3-0407-0	0	86	C	
{34CM3†	35.0	EV-0279-0	0	90	D	
{Model 6000 A:	No Adapter Required.					
34GD5	35.0	ET-2761-0	36	87	A 4500	
35B5	35.0	ET-1562-0	23	87	A 4500	
35C5	35.0	ET-2761-0	23	87	A 4500	
35EH5	35.0	ET-2761-0	10	89	A 5000	
35GL6	35.0	ET-2751-0	35	88	A 5300	

USE ADAPTER SA-8, 1050-168
USE ADAPTER SA-8, 1050-168
Pent. Sect.
Diode Sect.
Pent. Sect.
Triode Sect.

CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET
CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET
Pent. No. 1
Pent. No. 2

TRIODE NO. 1 MAKE "LINE TEST" AT 1350 ON 3000 SCALE
Triode No. 2
Diode No. 1
Diode No. 2

CONNECT JUMPER FROM CAP TO PIN 6 OF OCTAL SOCKET
CONNECT JUMPER FROM TUBE CAP TO PINS ON OCTAL SOCKET.

Pent. Sect.
Triode No. 1
Triode No. 2
CONNECT JUMPER FROM TUBE CAP TO PIN NO. 8 ON OCTAL SOCKET

USE ADAPTER SA-4, 1050-144. NOTE 3

Pent. Sect.
Diode Sect.
Pent. Sect.
Diode Sect.

Pent. Sect.
Diode Sect.
Pent. Sect.
Diode Sect.

USE ADAPTER SA-4, 1050-144. NOTE 3

PLATE TO SCREEN SHORT NORMAL USE ADAPTER SA-4, 1050-144. NOTE 3

6EV7	6.3	EV-2103-0	10	84	A	3600	Triode No. 2	1222	6.3	GR-4237-8	17	88	A	5000		
6EW6	6.3	ET-1562-7	11	84	A	3700		2050	6.3	HS-5308-6	*	94	F	-----	Strikes at about 25	
6EW7	6.3	EV-7608-0	27	72	A	2000	Triode No. 1	2051	6.3	HS-5308-6	*	94	F	-----	Strikes at about 25	
6EW7	6.3	EV-2109-0	54	88	A	6000	Triode No. 2	4604	6.3	CX-5X30-0	38	87	A	4500		
6EX6	6.3	HS-5X83-0	48	91	A	7500		5636	6.3	DW-1572-4	13	67	A	1600	Grid No. 1	
		Tubes indicating shorts: Re-test using HS-5X13-0							5636	6.3	DW-4578-1	22	0	B	500	Grid No. 2
6EY6	6.3	HS-5348-0	28	87	A	4400		5642	1.1	BS-0X00-0	0	0	D	-----	CONNECT FIL. LEADS TO PINS 1 AND 2. OK ABOVE 200 ON 3000 SCALE	
6EZ5	6.3	HS-5348-0	51	71	A	1800		5643	6.3	DW-7105-2	*	85	D	-----	Strikes at about 78	
6EZ8	6.3	EV-9800-0	28	78	A	2500	Triode No. 1	5654	6.3	ET-1562-0	24	65	A	1500		
6EZ8	6.3	EV-7600-0	28	78	A	2500	Triode No. 2	5670	6.3	KR-7608-0	16	86	A	4000	Triode No. 1	
6EZ8	6.3	EV-2301-0	18	78	A	2500	Triode No. 3	5670	6.3	KR-3402-0	16	86	A	4000	Triode No. 2	
		If no reading is obtained, use selector setting FU- in place of EV-							5672	1.1	DV-4120-0	32	21	B	650	
6FA7	6.3	EV-7986-1	10	58	A	1250	Tetrode No. 1	5675	6.3	HS-3506-0	20	88	A	5000	USE HICKOK ADAPTER SA-9 CODE NO. 1050-121	
6FA7	6.3	EV-7186-9	10	58	A	1250	Tetrode No. 2	5676	1.1	ES-3100-0	26	62	A	1400		
6FA7	6.3	EV-9306-1	0	26	C	-----	Diode Sect.	5677	1.1	ES-3100-0	38	21	A	650		
6FD6	6.3	ET-1657-2	18	45	C	-----	OK ABOVE DIODES OK	5678	1.1	DV-4120-0	12	31	B	750		
6FD7	6.3	EV-7608-0	10	68	A	1600	Triode No. 1	5686	6.3	EV-2763-0	11	79	A	2600		
6FD7	6.3	EV-2109-0	58	89	A	4500	Triode No. 2	5687	12.6	EV-7906-1	26	91	A	7500	Triode No. 1	
6FE5	6.3	HS-5348-0	30	92	A	8300		5687	12.6	EV-2103-9	26	91	A	7500	Triode No. 2	
6FG5	6.3	ET-1567-0	10	82	A	2500		5696	6.3	ET-1602-5	*	94	F	-----	Strikes at about 25	
6FG7	6.3	EV-9678-0	10	82	A	3000	Pent. Sect.	5702	6.3	DU-7126-5	24	65	A	1500		
6FG7	6.3	EV-1203-0	18	88	A	4750	Triode Sect.	5703	6.3	DU-5106-0	26	81	A	3000		
6FH5	6.3	ET-2507-0	14	87	A	4600		5704	6.3	CT-0104-0	0	79	C	-----	Diode	
6FH8	6.3	EV-6970-0	25	78	A	2500	TETRODE PLATE NO. 1	5718	6.3	DW-1805-7	23	89	A	5500		
6FH8	6.3	EV-6870-0	22	60	A	1300	TETRODE PLATE NO. 2	5719	6.3	DW-1805-7	17	65	A	1500		
6FH8	6.3	EV-6170-0	22	60	A	1300	TETRODE PLATE NO. 3	5725	6.3	ET-1562-7	11	48	A	1000		
6FH8	6.3	EV-2300-0	23	90	A	5400	Triode Sect.	5726	6.3	ET-0701-6	0	78	C	-----	Diode No. 1	
		If no reading is obtained, use selector setting FU- in place of EV-							5726	6.3	ET-0205-6	0	78	C	-----	Diode No. 2
6FJ7†	6.3	B3-XA09-0	20	78	A	2300	Triode No. 1	5727	6.3	ET-1602-5	*	94	F	-----	Strikes at about 24	
6FJ7	6.3	B3-3507-0	16	91	A	7000	Triode No. 2	5744	6.3	CT-4105-0	16	73	A	2000		
6FM7†	6.3	B3-XA09-0	20	46	A	950	Triode No. 1	5749	6.3	ET-1567-2	11	72	A	1900		
6FM7	6.3	B3-8507-0	62	88	A	5250	Triode No. 2	5750	6.3	ET-7562-1	0	35	B	800	AMPL. SECT. MAKE NO GAS TEST	
6FM8	6.3	EV-8907-0	11	56	A	1200	Triode Sect.	5750	6.3	ET-1602-7	20	90	A	6500	OSC. SECT. MAKE GAS TEST	
6FM8	6.3	EV-0601-0	0	77	C	-----	Diode No. 1	5751	12.6	EV-7608-0	12	58	A	1250	Triode No. 1	
6FM8	6.3	EV-0203-0	0	77	C	-----	Diode No. 2	5751	12.6	EV-2103-0	12	58	A	1250	Triode No. 2	
6FQ5	6.3	ET-2507-0	19	87	A	4500		5755	12.6	EV-6807-3	11	31	A	750	Triode No. 1	
6FQ5A	6.3	ET-2507-0	19	89	A	5200		5755	12.6	EV-3102-6	11	31	A	750	Triode No. 2	
6FQ7	6.3	EV-7608-0	23	79	A	2600	Triode No. 1	5763	6.3	EV-9167-3	11	87	A	4500		
6FQ7	6.3	EV-2103-0	23	79	A	2600	Triode No. 2	5784	6.3	DU-7126-5	12	75	A	2200		
6FS5	6.3	ET-1567-0	10	85	A	3500		5814	12.6	EV-7608-0	16	80	A	2775	Triode No. 1	
6FV6	6.3	ET-1567-2	12	85	A	3800		5814	12.6	EV-2103-0	16	80	A	2775	Triode No. 2	
6FV8	6.3	EV-9678-0	10	80	A	2750	Pent. Sect.	5829	6.3	DV-0607-0	0	78	C	-----	Diode No. 1	
6FV8	6.3	EV-1203-0	15	89	A	5500	Triode Sect.	5829	6.3	DV-0102-0	0	78	C	-----	Diode No. 2	
6FW5	6.3	HS-1583-0	48	90	A	6200		5840	6.3	DW-1574-0	19	78	A	2500		
6FY7†	6.3	B3-XA09-0	20	32	A	800	Triode No. 1	5842	6.3	DZ-5106-0	19	93	A	8000		
6FY7	6.3	B3-3507-0	54	92	A	6500	Triode No. 2	5844	6.3	ET-5207-0	26	81	A	3000	Triode No. 1	
6FY8	6.3	EV-3672-0	22	89	A	5700	Pent. Sect.	5844	6.3	ET-6107-0	26	81	A	3000	Triode No. 2	
6FY8	6.3	EV-1908-0	21	62	A	1400	Triode Sect.	5847	6.3	DZ-1684-0	11	88	A	5000		
6G11†	6.3	B3-8AX9-0	19	89	A	5500	Pent. No. 1	5852	6.3	HS-0508-0	0	0	D	-----	Plate No. 1	
6G11	6.3	B3-3672-4	10	8	A	700	Pent. No. 2	5852	6.3	HS-0308-0	0	0	D	-----	Plate No. 2	
6GA7†	6.3	B3-4735-0	58	89	A	4500	Pent. Sect.	5876	6.3	HS-3506-0	10	84	A	3600	USE HICKOK ADAPTER SA-9 CODE NO. 1050-121	
6GA7	6.3	B3-0A08-0	0	85	D	-----	Diode Sect.	5881	6.3	HS-5348-1	17	88	A	5000		
6GC5	6.3	EV-6917-0	11	91	B	7500		5893	6.3	HS-3506-0	10	87	A	4600	USE HICKOK ADAPTER SA-9 CODE NO. 1050-121	
6GE5†	6.3	B3-A72X-0	48	90	A	6000		5896	6.3	DW-0507-4	0	80	D	-----	Plate No. 1	
6GE8	6.3	EV-8917-0	14	72	A	1850	Pent. Sect.	5896	6.3	DW-0102-4	0	80	D	-----	Plate No. 2	
6GE8	6.3	EV-3602-0	64	86	A	4700	Triode Sect.	5897	6.3	DW-1805-0	25	84	A	3600		
6GF5†	6.3	B3-A72X-0	54	88	A	4800		5899	6.3	DW-1574-0	19	73	A	2000		
6GF7†	6.3	EV-9801-0	19	35	A	700	TRIODE NO. 1 USE ADAPTER SA-4, 1050-144. NOTE 3	5900	6.3	DW-1574-0	19	73	A	2000		
6GF7	6.3	EV-2603-0	57	91	A	7200	Triode No. 2	5902	6.3	DW-1572-0	40	86	A	4200		
Model 6000 A:		No Adapter Required.							5903	25.0	DW-0507-4	0	80	D	-----	Plate No. 1

6GE8	6.3	EV-8917-0	14	72	A	1850	Pent. Sect.	5896	6.3	DW-0507-4	0	80	D	-----	Plate No. 1
6GE8	6.3	EV-3602-0	64	86	A	4700	Triode Sect.	5896	6.3	DW-0102-4	0	80	D	-----	Plate No. 2
6GF5†	6.3	B3-A72X-0	54	88	A	4800		5897	6.3	DW-1805-0	25	84	A	3600	
6GF7†	6.3	EV-9801-0	19	35	A	700	TRIODE NO. 1 USE ADAPTER SA-4, 1050-144. NOTE 3	5899	6.3	DW-1574-0	19	73	A	2000	
6GF7	6.3	EV-2603-0	57	91	A	7200	Triode No. 2	5900	6.3	DW-1574-0	19	73	A	2000	
Model 6000	A:	No Adapter Required.						5902	6.3	DW-1572-0	40	86	A	4200	
6GH8	6.3	EV-2637-0	11	82	A	3000	Pent. Sect.	5903	25.0	DW-0507-4	0	80	D	-----	Plate No. 1
6GH8	6.3	EV-9108-0	21	85	A	3900	Triode Sect.	5903	25.0	DW-0102-4	0	80	D	-----	Plate No. 2
6GJ5†	6.3	EV-6X73-0	28	91	B	6600	USE ADAPTER SA-4, 1050-144. NOTE 3	5904	25.0	DW-1805-0	36	73	A	2000	
Model 6000	A:	No Adapter Required.						5905	25.0	DW-1572-0	18	70	B	1800	
6GJ8	6.3	EV-2637-0	10	83	A	3000	Pent. Sect.	5906	25.0	DW-1572-0	13	81	A	3000	
6GJ8	6.3	EV-9108-0	10	84	A	3200	Triode Sect.	5907	25.0	DW-1572-0	15	75	B	2200	
6GK5	6.3	ET-2507-6	20	87	A	4400		5908	25.0	DW-1572-4	20	69	B	1750	
6GK6	6.3	EV-2781-3	10	90	A	5750		5915A	6.3	ET-1562-7	11	59	B	1300	Grid No. 1
6GL7	6.3	JX-4506-0	23	23	A	600	Triode No. 1	5915A	6.3	ET-7562-1	11	43	B	900	Grid No. 3
6GL7	6.3	JX-1203-0	57	90	A	6400	Triode No. 2	5916	25.0	DW-1572-4	20	67	A	1600	
6GM5	6.3	EV-6917-0	10	89	A	5100		5930	2.5	ER-3200-0	68	81	A	3000	
6GM6	6.3	ET-1562-7	10	86	A	5000		5931	5.0	JS-0600-0	0	45	D	-----	Plate No. 1
6GN8	6.3	EV-7986-0	10	90	A	6000	Pent. Sect.	5931	5.0	JS-0400-0	0	35	D	-----	Plate No. 2
6GN8	6.3	EV-2301-0	16	60	A	1300	Triode Sect.	5932	6.3	HS-5348-1	17	88	A	5000	
6GQ7	6.3	EV-0809-0	0	80	C	-----	Diode No. 1	5933	6.3	FR-3X24-0	25	85	A	3800	
6GQ7	6.3	EV-0607-0	0	80	C	-----	Diode No. 2	5963	12.6	EV-7608-0	24	75	A	2200	Triode No. 1
6GQ7	6.3	EV-0201-0	0	80	C	-----	Diode No. 3	5963	12.6	EV-2103-0	24	75	A	2200	Triode No. 2
6GT5†	6.3	EV-6973-0	28	91	B	6600	USE ADAPTER SA-4, 1050-144. NOTE 3	5964	6.3	ET-5207-6	21	85	A	4000	Triode No. 1
Model 6000	A:	No Adapter Required.						5964	6.3	ET-6107-5	21	85	A	4000	Triode No. 2
6GU5	6.3	ET-1562-0	13	89	A	5500		5965	12.6	EV-7608-1	16	90	A	6500	Triode No. 1
6GU7	6.3	EV-7608-0	30	75	A	2050	Triode No. 1	5965	12.6	EV-2103-6	16	90	A	6500	Triode No. 2
6GU7	6.3	EV-2103-0	30	75	A	2050	Triode No. 2	5971	1.1	FT-2100-0	20	65	A	1500	
6GV5†	6.3	B3-92A4-0	42	86	A	4500	DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 2 OF THE OCTAL SOCKET	5975	6.3	EV-3102-0	28	86	A	4000	
6GW6	6.3	HS-5X48-0	28	91	B	6600		5977	6.3	DW-1805-3	32	86	A	4000	
6GX6	6.3	ET-1562-7	12	67	A	1600		5987	6.3	DW-1205-0	74	71	A	1850	
6GX7	6.3	EV-2671-0	11	84	A	3200	Pent. Sect.	5995	6.3	ET-0105-0	0	55	D	-----	Leads-1-3-4-5
6GX7	6.3	EV-9801-0	18	89	A	4800	Triode Sect.	5998	6.3	HY-4506-2	56	92	A	8000	Triode No. 1
6GY5†	6.3	B3-527X-0	30	92	B	9000	DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 2 OF THE OCTAL SOCKET.	5998	6.3	HY-1203-5	56	92	A	8000	Triode No. 2
6GY6	6.3	ET-1562-7	14	61	A	1350		6005	6.3	ET-1562-0	11	86	A	4100	
6GY8	6.3	EV-0607-0	0	79	C	-----	Triode No. 1	6012	6.3	HS-3501-8	#	94	F	-----	Strikes at about 25
6GY8	6.3	FU-3908-0	20	75	A	2250	Triode No. 2	6021	6.3	DW-7805-0	25	78	A	2500	Triode No. 1
6GY8	6.3	FU-1200-0	29	75	A	2250	Triode No. 3	6021	6.3	DW-2104-0	25	78	A	2500	Triode No. 2
6GZ5	6.3	ET-2761-0	20	86	A	4000		6028	20.0	ET-1562-0	24	65	A	1500	
6HA5	6.3	ET-1507-6	20	87	A	4600		6046	25.0	HS-5348-1	33	88	A	5200	
6HA6	6.3	EV-2761-3	10	90	A	6500		6050	1.1	ES-3100-0	28	60	A	1300	
6HB5†	6.3	B3-A72X-0	57	89	A	5600		6051	1.1	DV-4120-0	39	0	B	600	
6HB6	6.3	EV-2781-9	10	92	A	7500		6052	6.3	DW-0507-4	0	80	D	-----	Plate No. 1
6HB7	6.3	EV-2671-0	10	79	A	3100	Pent. Sect.	6052	6.3	DW-0102-4	0	80	D	-----	Plate No. 2
6HB7	6.3	EV-9801-0	11	89	A	4500	Triode Sect.	6053	25.0	DW-0507-4	0	80	D	-----	Plate No. 1
6H-B25	6.3	EV-2X79-8	50	87	A	4500	USE ADAPTER SA-3, 1050-168	6053	25.0	DW-0102-4	0	80	D	-----	Plate No. 2
6HC8	6.3	EV-3672-0	15	88	A	5100	Pent. Sect.	6055	25.0	DW-1805-0	36	73	A	2000	
6HC8	6.3	EV-1908-0	9	73	A	2000	Triode Sect.	6056	25.0	DW-1572-0	15	75	B	2200	
6HD5†	6.3	B3-A79X-0	54	89	A	6000		6058	6.3	ET-0701-6	0	78	C	-----	Diode No. 1
6HD7	6.3	EV-2671-0	10	79	A	2800	Pent. Sect.	6058	6.3	ET-0205-6	0	78	C	-----	Diode No. 2
6HD7	6.3	EV-9803-0	15	90	A	7000	Triode Sect.	6072	12.6	EV-7608-0	18	58	A	1250	Triode No. 1
6HE5†	6.3	B3-96XA-0	23	87	A	4500		6072	12.6	EV-2103-0	18	58	A	1250	Triode No. 2
6HE7†	6.3	B3-95A8-0	54	91	A	7000	Pent. Sect.	6080	7.5	HY-4506-2	100	83	A	3400	Triode No. 1
6HE7	6.3	B3-0204-0	0	86	C	-----	Diode Sect.	6080	7.5	HY-1203-5	100	83	A	3400	Triode No. 2
6HF5†	6.3	B3-92A4-0	75	88	A	4300	DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 2 OF THE OCTAL SOCKET.	6082	25.0	HY-4506-2	100	83	A	3400	Triode No. 1
6HF8	6.3	EV-7986-0	10	88	A	4800	Pent. Sect.	6082	25.0	HY-1203-5	100	83	A	3400	Triode No. 2
								6084	6.3	EV-9613-8	18	71	A	1850	
								6085	12.6	EV-7608-0	18	80	A	2700	Triode No. 1
								6085	12.6	EV-2103-0	18	80	A	2700	Triode No. 2
								6086	20.0	EV-2613-9	10	90	A	6500	
									6.3	ET-1562-0	04	65	A	1500	

{6HE7†	6.3	B3-95A8-0	54	91	A	7000	Pent. Sect.	6082	25.0	EV-1203-0	100	83	A	3400	
{6HE7	6.3	B3-0204-0	0	86	C	-----	Diode Sect.	6084	6.3	EV-9613-8	18	71	A	1850	Triode No. 1
6HF5†	6.3	B3-92A4-0	75	88	A	4300	DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 2 OF THE OCTAL SOCKET.	{6085	12.6	EV-7608-0	18	80	A	2700	Triode No. 2
{6HF8	6.3	EV-7986-0	10	88	A	4800	Pent. Sect.	6085	12.6	EV-2103-0	18	80	A	2700	Triode No. 2
{6HF8	6.3	EV-2301-0	20	69	A	1700	Triode Sect.	6086	20.0	EV-2613-9	10	90	A	6500	
6HG5	6.3	ET-1562-0	11	86	A	4100		6096	6.3	ET-1562-0	24	65	A	1500	
{6HG8	6.3	EV-2893-0	10	84	A	3600	Pent. Sect.	{6097	6.3	ET-0701-6	0	78	C	-----	Diode No. 1
{6HG8	6.3	EV-6703-0	32	82	A	3200	Triode Sect.	6097	6.3	ET-0205-6	0	78	C	-----	Diode No. 2
6HJ5†	6.3	B3-A792-X	54	90	A	6500		6098	6.3	GY-7351-0	21	89	A	5400	
{6HJ7	6.3	EV-2671-0	10	89	A	4000	Pent. Sect.	{6110	6.3	DW-0507-4	0	74	C	-----	Diode No. 1
{6HJ7	6.3	EV-9803-0	20	91	A	4500	Triode Sect.	6110	6.3	DW-0102-4	0	74	C	-----	Diode No. 2
{6HJ8	6.3	EV-2631-9	10	85	A	3500	Pent. Sect.	{6111	6.3	DW-7805-0	26	86	A	4000	Triode No. 1
{6HJ8	6.3	EV-0807-0	0	79	C	-----	Diode Sect.	6111	6.3	DW-2104-0	26	86	A	4000	Triode No. 2
6HK5	6.3	ET-1502-0	19	88	A	5000		{6112	6.3	DW-7805-0	20	65	A	1500	Triode No. 1
6HL5	6.3	EV-2793-0	15	93	A	9500		6112	6.3	DW-2104-0	20	65	A	1500	Triode No. 2
{6HL8	6.3	EV-2637-0	10	87	A	4400	Pent. Sect.	6134	6.3	HS-4865-3	11	81	A	3000	
{6HL8	6.3	EV-9108-0	18	87	A	4400	Triode Sect.	6135	6.3	ET-6107-0	25	75	A	2200	
6HM5	6.3	ET-1507-6	20	87	A	4600		6136	6.3	ET-1567-2	11	76	A	2300	
6HM6	6.3	EV-2781-9	11	87	A	4700		6137	6.3	HS-4865-3	12	73	A	2000	
6HQ5	6.3	ET-1507-6	20	87	A	4400		6146	6.3	HS-5X31-8	45	88	A	5000	
6HR5	6.3	ET-1562-0	10	87	A	4500		6148	6.3	DU-7126-5	24	65	A	1500	
6HR6	6.3	ET-1567-2	10	84	A	3600		6152	6.3	EV-3102-0	28	86	A	4000	
6HS5†	6.3	B3-2704-3	0	88	A	4500		6159	25.0	HS-5X31-8	45	88	A	5000	
6HS6	6.3	ET-1567-2	14	82	A	3200		6186	6.3	ET-1562-0	11	78	A	2500	
{6HS8	6.3	EV-7821-9	10	15	A	600	Pent. No. 1	{6189	12.6	EV-7608-0	24	75	A	2200	Triode No. 1
{6HS8	6.3	EV-7321-6	10	15	A	600	Pent. No. 2	6189	12.6	EV-2103-0	24	75	A	2200	Triode No. 2
6HT6	6.3	EV-2781-9	10	87	A	4600		6197	6.3	EV-2631-7	11	88	A	5000	
6HV5†	6.3	B3-7204-3	0	82	C	-----		{6201	12.6	EV-7608-0	11	82	A	3000	Triode No. 1
{6HW8	6.3	EV-6X37-9	13	72	A	1900		6201	12.6	EV-2103-0	11	82	A	3000	Triode No. 2
Make external connection from Pin 2 and 8 of octal socket to plate cap lead. Connect Pin 1 to Pin 7 in octal socket.								{6202	6.3	ET-0607-1	0	25	D	-----	Plate No. 1
6HZ6	6.3	ET-1562-7	10	65	A	1400		6202	6.3	ET-0107-6	0	25	D	-----	Plate No. 2
{6HZ8	6.3	EV-7986-0	16	88	A	5000	Pent. Sect.	6203	6.3	EV-0907-1	0	40	D	-----	Plate No. 1
{6HZ8	6.3	EV-2301-0	18	76	A	2300	Triode Sect.	6203	6.3	EV-0107-9	0	40	D	-----	Plate No. 2
6J4	6.3	ET-1702-0	20	90	A	6000		6205	6.3	DW-1572-4	19	78	A	2500	
{6J6	6.3	ET-5207-0	21	81	A	3000	Triode No. 1	6206	6.3	DW-1572-4	19	73	A	2000	
{6J6	6.3	ET-6107-0	21	81	A	3000	Triode No. 2	{6211	12.6	EV-7608-2	24	84	A	3600	Triode No. 1
{6J9†	6.3	EV-780X-0	17	81	A	3000	Triode No. 1	6211	12.6	EV-2103-7	24	84	A	3600	Triode No. 2
{6J9	6.3	EV-960X-0	17	81	A	3000	Triode No. 2	6216	6.3	EV-2173-0	20	92	A	9000	
{6J9	6.3	EV-2103-0	17	81	A	3000	Triode No. 3	6221	6.3	DW-1805-0	23	84	A	3500	
{6J10†	6.3	B3-7468-5	6	27	B	700	Pent. No. 1	6222	6.3	DW-1805-0	22	21	A	650	
{6J10	6.3	B3-A923-0	16	88	A	4350	Pent. No. 2	6223	6.3	DW-1578-0	15	78	A	2500	
{6J11†	6.3	B3-A978-X	10	86	A	4000	Pent. No. 1	6225	6.3	DW-1572-0	11	82	A	3100	
{6J11	6.3	B3-5326-4	10	86	A	4000	Pent. No. 2	6245	6.3	DU-7126-5	24	65	A	1500	
6JB5†	6.3	B3-96XA-0	51	71	A	1800		6247	6.3	DW-2805-0	11	73	A	2000	
{6JB6†	6.3	EV-2X13-8	28	91	B	6600	USE ADAPTER SA-4, 1050-144, NOTE 3	6263	6.3	HS-3506-0	18	88	A	5000	USE HICKOK ADAPTER SA-9 CODE NO. 1090-121
{Model 6000	A:	No Adapter Required.						6264	6.3	HS-3506-0	10	87	A	4600	USE HICKOK ADAPTER SA-9 CODE NO. 1090-121
{6JB8	6.3	EV-2637-0	25	45	A	1000	Pent. Sect.	6265	6.3	ET-1562-7	12	73	A	2000	
{6JB8	6.3	EV-9108-0	19	77	A	2400	Triode Sect.	6286	1.4	ES-3100-0	42	62	A	1400	
6JC6	6.3	EV-2781-9	11	88	A	5000		6293	6.3	HS-5X31-0	24	90	A	6500	
{6JC8	6.3	EV-2637-0	10	82	A	3000	Pent. Sect.	{6350	12.6	EV-8607-3	26	87	A	4600	Triode No. 1
{6JC8	6.3	EV-8901-0	10	89	A	5000	Triode Sect.	6350	12.6	EV-3102-8	26	87	A	4600	Triode No. 2
6JD6	6.3	EV-2781-9	10	83	A	3200		6384	6.3	GY-7351-0	21	89	A	5400	
{6JE6†	6.3	EV-2X73-8	39	92	B	8100	USE ADAPTER SA-4, 1050-144, NOTE 3	{6386	6.3	KR-7608-5	24	86	A	4000	Triode No. 1
{Model 6000	A:	No Adapter Required.						6386	6.3	KR-3402-5	24	86	A	4000	Triode No. 2
{6JE8	6.3	EV-7986-0	11	89	A	5000	Pent. Sect.	6397	2.5	HR-8360-0	33	72	A	1950	
{6JE8	6.3	EV-2301-0	12	75	A	2200	Triode Sect.	{6414	12.6	EV-7608-0	17	84	A	3500	Triode No. 1
{6JF6†	6.3	EV-2X73-8	32	92	B	7800	USE ADAPTER SA-4, 1050-144, NOTE 3	6414	12.6	EV-2103-0	17	84	A	3500	Triode No. 2
{Model 6000	A:	No Adapter Required.						6417	12.6	EV-9167-3	11	87	A	4500	
								6418	1.4	DV-0204-1	0	0	C	-----	OK ABOVE 300 ON 3000 SCALE
								{6463	12.6	EV-8607-1	25	88	A	5200	Triode No. 1
								6463	12.6	EV-3102-6	25	88	A	5200	Triode No. 2

{6JE6†	6.3	EV-2X73-8	39	92	B	8100	USE ADAPTER SA-4, 1050-144. NOTE 3	{6414	12.6	EV-7608-0	17	84	A	3500	Triode No. 1
{Model 6000	A:	No Adapter Required.						{6414	12.6	EV-2103-0	17	84	A	3500	Triode No. 2
{6JE8	6.3	EV-7986-0	11	89	A	5000	Pent. Sect.	{6417	12.6	EV-9167-3	11	87	A	4500	
{6JE8	6.3	EV-2301-0	12	75	A	2200	Triode Sect.	6418	1.4	DV-0204-1	0	0	C	-----	OK ABOVE 300 ON 3000 SCALE
{6JF6†	6.3	EV-2X73-8	32	92	B	7800	USE ADAPTER SA-4, 1050-144. NOTE 3	{6463	12.6	EV-8607-1	25	88	A	5200	Triode No. 1
{Model 6000	A:	No Adapter Required.						{6463	12.6	EV-3102-6	25	88	A	5200	Triode No. 2
{6JF8	6.3	HR-5X46-0	25	90	B	6050	Pent. Sect.	{6485	6.3	ET-1567-2	11	81	A	3000	
{6JF8	6.3	HR-0802-0	0	85	D	-----	Diode Sect.	6519	1.4	DV-4210-0	0	0	C	-----	OK OVER 850 ON 3000 SCALE
{6JG6†	6.3	EV-2973-6	32	92	B	7800	USE ADAPTER SA-4, 1050-144. NOTE 3	{6520	7.5	HY-4506-2	100	79	A	2600	Triode No. 1
{Model 6000	A:	No Adapter Required.						{6520	7.5	HY-1203-5	100	79	A	2600	Triode No. 2
{6JH6	6.3	ET-1562-7	11	84	A	3700		6526	1.1	DV-4120-0	20	61	B	1250	
{6JH8	6.3	EV-6937-1	23	57	A	1200	PLATE NO. 1. DISREGARD NEON FLASH IN SHORT TESTING.	6533	6.3	GX-2105-0	20	53	A	1100	
{6JH8	6.3	EV-6837-1	23	57	A	1200	PLATE NO. 2. DISREGARD NEON FLASH IN SHORT TESTING.	6540	6.3	DU-7126-5	24	65	A	1500	
{6JK6	6.3	ET-1562-7	10	86	A	4800		6611	1.4	DV-0204-1	0	0	C	-----	OK ABOVE 500 ON 3000 SCALE
{6JK8	6.3	EV-7608-9	23	78	A	2000	Triode No. 1	6612	1.4	DV-0204-1	0	0	C	-----	
{6JK8	6.3	EV-2103-9	20	89	A	5000	Triode No. 2	6659	OFF	AP-0105-0	0	40	G	-----	Leads=1-5
{6JL6	6.3	ET-1562-7	16	85	A	4200		{6660	6.3	ET-1567-2	11	72	A	1900	
{6JL8	6.3	EV-7986-0	10	88	A	5200	Pent. Sect.	{6661	6.3	ET-1562-7	12	73	A	2000	
{6JL8	6.3	EV-2301-0	17	81	A	2900	Triode Sect.	{6662	6.3	ET-1562-7	11	72	A	1900	
{6JM6†	6.3	B3-5632-4	43	91	A	7000	CONNECT JUMPER FROM TUBE CAP TO PIN NO. 8 ON OCTAL SOCKET.	{6663	6.3	ET-0701-6	0	78	C	-----	Diode No. 1
{6JN6†	6.3	B3-A732-4	43	91	A	7000		{6663	6.3	ET-0205-6	0	78	C	-----	Diode No. 2
{6JN8	6.3	EV-9678-0	10	82	A	3200	Pent. Sect.	6664	6.3	ET-6107-0	11	81	A	3000	
{6JN8	6.3	EV-1203-0	17	89	A	5500	Triode Sect.	6669	6.3	ET-1562-0	11	86	A	4100	
{6JQ6	6.3	EV-7139-6	50	85	A	3800	Pent. Sect.	6676	6.3	ET-1562-7	11	81	A	3000	
{6JQ6	6.3	EV-0609-0	0	70	C	-----	Diode Sect.	6677	6.3	EV-2631-7	11	88	A	5000	
{6JR6†	6.3	EV-2913-6	65	85	A	4200	USE ADAPTER SA-4, 1050-144. NOTE 3	{6678	6.3	EV-2637-0	11	73	A	2000	Pent. Sect.
{Model 6000A:	No adapter required.							{6678	6.3	EV-9108-0	12	90	A	6200	Triode Sect.
{6JS6A†	6.3	B3-5632-4	53	88	A	4300	CONNECT JUMPER FROM TUBE CAP TO PIN NO. 8 ON OCTAL SOCKET. USE ADAPTER SA-4, 1050-144. NOTE 3	{6679	12.6	EV-7608-0	11	81	A	3000	Triode No. 1
{6JT6†	6.3	EV-2973-6	44	91	A	7000		{6679	12.6	EV-2103-0	11	81	A	3000	Triode No. 2
{Model 6000	A:	No Adapter Required.						{6680	12.6	EV-7608-0	24	75	A	2200	Triode No. 1
{6JT8	6.3	EV-7986-0	12	90	A	6000	Pent. Sect.	{6680	12.6	EV-2103-0	24	75	A	2200	Triode No. 2
{6JT8	6.3	EV-2301-0	20	46	A	950	Triode Sect.	{6681	12.6	EV-7608-0	12	58	A	1250	Triode No. 1
{6JU6†	6.3	EV-2X13-8	72	85	A	4200	USE ADAPTER SA-4, 1050-144. NOTE 3	{6681	12.6	EV-2103-0	12	58	A	1250	Triode No. 2
{Model 6000	A:	No Adapter Required.						6688	6.3	EV-2791-8	11	81	A	3000	
{6JU8	6.3	EV-0809-0	0	78	C	-----	Diode No. 1	{6690	6.3	DW-7508-0	22	78	A	2500	Triode No. 1
{6JU8	6.3	EV-0708-0	0	78	C	-----	Diode No. 2	{6690	6.3	DW-2104-0	22	78	A	2500	Triode No. 2
{6JU8	6.3	EV-0203-0	0	78	C	-----	Diode No. 3	{6754	6.3	EV-0907-0	0	80	D	-----	Plate No. 1
{6JU8	6.3	EV-0102-0	0	78	C	-----	Diode No. 4	{6754	6.3	EV-0103-0	0	80	D	-----	Plate No. 2
{6JV6†	6.3	B3-A732-X	55	91	A	7000		6788	6.3	DW-1572-0	13	41	A	900	
{6JV8	6.3	EV-7986-0	7	89	A	3700	Pent. Sect.	6814	6.3	DW-1805-0	24	87	A	4500	
{6JV8	6.3	EV-2301-0	20	69	A	1680	Triode Sect.	{6829	12.6	EV-7608-0	16	90	A	6700	Triode No. 1
{6JY8	6.3	EV-7986-0	18	86	A	4500	Pent. Sect.	{6829	12.6	EV-2103-0	16	90	A	6700	Triode No. 2
{6JY8	6.3	EV-2301-0	18	86	A	5000	Triode Sect.	{6832	6.3	DW-7805-0	27	51	A	1050	Triode No. 1
{6JZ6†	6.3	B3-5632-4	56	91	A	7000	CONNECT A JUMPER FROM CAP TO PIN 6 OF OCTAL SOCKET	{6832	6.3	DW-2104-0	27	51	A	1050	Triode No. 2
{6JZ8†	6.3	B3-7489-0	25	88	A	3900	Pent. Sect.	6872	6.3	DU-7126-5	14	76	A	2300	
{6JZ8	6.3	B3-X20A-0	29	65	A	1350	Triode Sect.	6883	12.6	HS-5X31-8	45	88	A	5000	
{6K6	6.3	HS-5348-0	34	67	A	1600		{6887	6.3	ET-0701-0	0	83	C	-----	Diode No. 1
{6K11†	6.3	B3-9X04-8	24	75	A	2200	Triode No. 1	{6887	6.3	ET-0205-0	0	83	C	-----	Diode No. 2
{6K11	6.3	B3-7506-8	12	58	A	1250	Triode No. 2	6889	6.3	GY-7X51-0	21	89	A	5400	
{6K11	6.3	B3-A203-8	12	58	A	1250	Triode No. 3	{6900	12.6	EV-7906-1	26	91	A	7500	Triode No. 1
{6KA8	6.3	EV-6983-7	16	70	A	1800	Pent. Sect.	{6900	12.6	EV-2103-9	26	91	A	7500	Triode No. 2
{6KA8	6.3	EV-2103-0	19	73	A	2000	Triode Sect.	{6919	6.3	ET-0701-6	0	78	C	-----	Diode No. 1
{6KD6†	6.3	B3-5632-4	70	90	A	7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET.	{6919	6.3	ET-0205-6	0	78	C	-----	Diode No. 2
{6KD8	6.3	EV-2637-0	10	79	A	2600	Pent. Sect.	{6922	6.3	EV-7608-0	24	89	A	5500	Triode No. 1
{6KD8	6.3	EV-9108-0	19	89	A	5200	Triode Sect.	{6922	6.3	EV-2103-0	24	89	A	5500	Triode No. 2
{6KE8	6.3	EV-2637-0	11	85	A	3700	Pent. Sect.	6943	6.3	DW-1572-4	14	76	A	2400	
{6KE8	6.3	EV-2103-0	20	87	A	1500	Triode Sect.	6944	6.3	DW-1572-4	13	76	A	2300	
{6KF8	6.3	EV-2103-0	20	87	A	1500	Triode Sect.	6945	6.3	DW-1572-0	41	83	A	3200	
{6KF8	6.3	EV-2103-0	20	87	A	1500	Triode Sect.	6946	6.3	DW-1805-0	24	85	A	3800	
{6KF8	6.3	EV-2103-0	20	87	A	1500	Triode Sect.	{6947	6.3	DW-7805-0	20	79	A	2600	Triode No. 1
{6KF8	6.3	EV-2103-0	20	87	A	1500	Triode Sect.	{6947	6.3	DW-2104-0	20	79	A	2600	Triode No. 2

6KD6†	6.3	B3-5632-4	70	90	A	7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET.	6943	6.3	DW-1572-4	14	76	A	2400		
{6KD8	6.3	EV-2637-0	10	79	A	2600	Pent. Sect.	6944	6.3	DW-1572-4	13	76	A	2300		
{6KD8	6.3	EV-9108-0	19	89	A	5200	Triode Sect.	6945	6.3	DW-1572-0	41	83	A	3200		
{6KE8	6.3	EV-2637-0	11	85	A	3700	Pent. Sect.	6946	6.3	DW-1805-0	24	85	A	3800		
{6KE8	6.3	EV-9108-0	20	87	A	4500	Triode Sect.	{6947	6.3	DW-7805-0	20	79	A	2600	Triode No. 1	
{6KF8	6.3	EV-7821-9	10	17	A	700	Pent. No. 1	{6947	6.3	DW-2104-0	20	79	A	2600	Triode No. 2	
{6KF8	6.3	EV-7321-6	10	17	A	700	Pent. No. 2	{6948	6.3	DW-7805-0	18	68	A	1650	Triode No. 1	
{6KL8	6.3	EV-2763-1	5	71	B	1700	Pent. Sect.	{6948	6.3	DW-2104-0	18	68	A	1650	Triode No. 2	
{6KL8	6.3	EV-0803-0	0	33	C	-----	DIODE SECT. OK ABOVE DIODES OK USE ADAPTER SA-4, 1050-144. NOTE 3	6973	6.3	EV-3917-0	10	85	A	4000		
{6KM6†	6.3	EV-2X73-8	65	89	A	5000	-----	{7025	12.6	EV-7608-0	12	58	A	1250	Triode No. 1	
Model 6000	A: No Adapter Required.								{7025	12.6	EV-2103-0	12	58	A	1250	Triode No. 2
{6KM8	6.3	EV-7986-0	5	50	B	950	TETRODE PLATE NO. 1	7027	6.3	HS-5318-0	17	88	A	5000		
{6KM8	6.3	EV-7286-0	5	53	B	1000	TETRODE PLATE NO. 2	{7036	6.3	ET-1562-7	11	42	B	900	Grid No. 1	
{6KM8	6.3	EV-7186-0	5	53	B	1000	TETRODE PLATE NO. 3	{7036	6.3	ET-7562-1	11	35	B	800	Grid No. 3	
{6KM8	6.3	EV-0306-0	0	35	C	-----	DIODE SECT. OK ABOVE DIODES OK DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 6 OF OCTAL SOCKET	{7044	12.6	EV-7906-0	26	90	A	6000	Triode No. 1	
{6KN6†	6.3	B3-5632-4	60	88	A	4500	-----	{7044	12.6	EV-2103-0	26	90	A	6000	Triode No. 2	
{6KR8	6.3	EV-7986-0	14	91	A	4750	Pent. Sect.	7054	12.6	EV-2781-3	11	87	A	4500		
{6KR8	6.3	EV-2301-0	17	91	B	3900	Triode Sect.	{7055	12.6	ET-0701-6	0	78	C	-----	Diode No. 1	
{6KS8	6.3	EV-7986-0	16	87	A	4500	Pent. Sect.	{7055	12.6	ET-0205-6	0	78	C	-----	Diode No. 2	
{6KS8	6.3	EV-2301-0	20	69	A	1700	Triode Sect.	7056	12.6	ET-1562-7	11	81	A	3000		
6KT6	6.3	EV-2781-9	15	81	A	2350		{7057	12.6	EV-7608-9	16	87	A	4500	Triode No. 1	
{6KT8	6.3	EV-7986-0	10	85	A	4000	Pent. Sect.	{7057	12.6	EV-2103-9	16	87	A	4500	Triode No. 2	
{6KT8	6.3	EV-2301-0	20	29	A	1700	Triode Sect.	{7058	12.6	EV-7608-0	12	58	A	1250	Triode No. 1	
{6KU8	6.3	EV-7986-0	14	90	A	5500	Pent. Sect.	{7058	12.6	EV-2103-0	12	58	A	1250	Triode No. 2	
{6KU8	6.3	EV-0301-0	0	26	C	-----	Diode No. 1	{7059	12.6	EV-2637-0	11	73	A	2000	Pent. Sect.	
{6KU8	6.3	EV-0201-0	0	26	C	-----	Diode No. 2	{7059	12.6	EV-9108-0	12	90	A	6200	Triode Sect.	
{6KV6†	6.3	EV-2973-6	41	87	B	4800	USE ADAPTER SA-4, 1050-144. NOTE 3	{7060	12.6	EV-8679-0	9	84	A	3000	Pent. Sect.	
Model 6000A	A: No Adapter Required.								{7060	12.6	EV-2103-0	13	83	A	2800	Triode Sect.
{6KV8	6.3	EV-7986-0	11	91	A	7400	Pent. Sect.	7061	12.6	EV-3917-0	11	86	A	4100		
{6KV8	6.3	EV-2301-0	19	72	A	1900	Triode Sect.	{7119	12.6	EV-7906-0	24	94	A	10000	Triode No. 1	
6KY6	6.3	EV-2781-3	17	88	A	5000		{7119	12.6	EV-2103-0	24	94	A	10000	Triode No. 2	
{6KY8†	6.3	EV-2673-0	41	88	A	5000	PENT. SECT. USE ADAPTER SA-4, 1050-144. NOTE 3	7137	6.3	ET-6702-0	20	90	A	6000		
{6KY8	6.3	EV-9801-0	22	15	A	600	Triode Sect.	7167	12.6	ET-1562-0	11	81	B	3000		
Model 6000	A: No Adapter Required.								7189	6.3	EV-2793-0	11	90	A	6000	
{6KZ8	6.3	EV-2673-0	12	82	A	3200	Pent. Sect.	{7199	6.3	EV-7236-0	7	82	A	2500	Pent. Sect.	
{6KZ8	6.3	EV-9108-0	22	84	A	3600	Triode Sect.	{7199	6.3	EV-9108-0	27	75	A	2100	Triode Sect.	
6L6	6.3	HS-5348-1	17	88	A	5000		7212	6.3	HS-5X31-8	45	88	A	5000		
6LB6†	6.3	B3-5632-4	36	91	B	9650	CAP=P. CONNECT CAP OF TUBE TO PIN 6 OF OCTAL SOCKET	7233	6.3	EV-2908-0	0	49	C	-----	OK ABOVE DIODES OK	
{6LB8	6.3	EV-7986-0	14	89	A	5300	Pent. Sect.	7239	6.3	EV-1X69-7	28	73	A	2100		
{6LB8	6.3	EV-2301-0	17	84	A	3600	Triode Sect.	{7247	12.6	EV-7608-0	12	58	A	1250	Triode No. 1	
6LC6	6.3	HS-0506-1	0	45	C	-----		{7247	12.6	EV-2103-0	25	75	A	2200	Triode No. 2	
{6LC8	6.3	EV-6987-3	16	70	A	1800	Pent. Sect.	{7258	12.6	EV-8679-1	10	85	A	3700	Pent. Sect.	
{6LC8	6.3	EV-2103-0	19	73	A	2000	Triode Sect.	{7258	12.6	EV-2173-6	19	87	A	4400	Triode Sect.	
{6LE8	6.3	EV-9683-7	10	65	A	1500	Pent. No. 1	{7308	6.3	EV-7608-0	24	89	A	5500	Triode No. 1	
{6LE8	6.3	EV-9183-2	10	65	A	1500	Pent. No. 2	{7308	6.3	EV-2103-0	24	89	A	5500	Triode No. 2	
{6LF8	6.3	EV-7986-0	5	90	A	3500	Pent. Sect.	{7316	12.6	EV-7608-0	24	75	A	2200	Triode No. 1	
{6LF8	6.3	EV-2301-0	19	64	A	1350	Triode Sect.	{7316	12.6	EV-2103-0	24	75	A	2200	Triode No. 2	
6LG6†	6.3	B3-58A4-X	64	86	A	4650	CAP=P. CONNECT CAP OF TUBE TO PIN 6 OF OCTAL SOCKET	7355	6.3	HS-6385-0	12	91	A	7600		
6LH6	6.3	HS-0506-1	0	45	C	-----		7357	25.0	HS-5X31-8	45	88	A	5000		
6LJ6	6.3	HS-0506-3	0	45	C	-----		7358	6.3	HS-5X31-8	23	91	A	7000		
{6LJ8	6.3	EV-9678-0	15	75	A	2700	Pent. Sect.	7360	6.3	EV-3621-9	18	50	A	1000	CONNECT PIN 1 TO PIN 8 AND PIN 6 TO PIN 7 ON OCTAL SOCKET	
{6LJ8	6.3	EV-1203-0	24	75	A	2500	Triode Sect.	{7370	20.0	FY-7906-0	26	91	A	7500	Triode No. 1	
{6LM8	6.3	EV-2637-0	13	82	A	3000	Pent. Sect.	{7370	20.0	JU-2103-0	26	91	A	7500	Triode No. 2	
{6LM8	6.3	EV-9108-0	18	88	A	4700	Triode Sect.	7408	6.3	HS-5348-1	13	86	A	4100		
6LQ6†	6.3	EV-2X73-8	39	92	B	8100	USE ADAPTER SA-4 1050-144. NOTE 3	7543	6.3	ET-1567-2	11	76	A	2300		
Model 6000A	A: No Adapter Required.								7551	12.6	EV-2631-7	17	90	A	6000	
								7558	6.3	EV-2631-7	17	90	A	6000		
								7581	6.3	HS-5348-0	17	88	A	6000		
								{7586†	6.3	DR-4208-0	28	78	A	2500	USE ADAPTER SA-3, 1050-127. NOTE 3	
								Model 6000	A:							

6LJ6	6.3	HS-0506-3	0	45	C	2700	Pent. Sect.	7551	12.6	EV-2631-7	17	90	A	6000	
6LJ8	6.3	EV-9678-0	15	75	A	2500	Triode Sect.	7558	6.3	EV-2631-7	17	90	A	6000	
6LJ8	6.3	EV-1203-0	24	75	A	3000	Pent. Sect.	7581	6.3	HS-5348-0	17	88	A	6000	
6LM8	6.3	EV-2637-0	13	82	A	4700	Triode Sect.	7586†	6.3	DR-4208-0	28	78	A	2500	USE ADAPTER SA-3, 1050-127. NOTE 3
6LM8	6.3	EV-9108-0	18	88	A	8100	USE ADAPTER SA-4 1050-144. NOTE 3	Model 6000 A:							
6LQ6†	6.3	EV-2X73-8	39	92	B			7586	6.3	13-4208-0	28	78	A	2500	
Model 6000A:	No Adapter Required.														
6LQ8	6.3	EV-7986-0	11	91	A	7400	Pent. Sect.	7587†	6.3	DR-4X28-0	11	85	B	3800	USE ADAPTER SA-3, 1050-127. NOTE 3
6LQ8	6.3	EV-2301-0	17	90	A	6500	Triode Sect.	Model 6000 A:							
6LR6†	6.3	B3-5832-4	85	73	A	2250	CONNECT JUMPER FROM TUBE CAP TO PIN 8 ON OCTAL SOCKET. PENT. SECT. USE ADAPTER SA-4, 1050-144. NOTE 3	7587	6.3	13-4528-0	11	85	B	3800	
6LR8†	6.3	EV-2673-0	40	87	A	4000	Triode Sect.	"Do not use tester cap connection. Jumper plate cap to Pin 5 of octal socket."							
6LR8	6.3	EV-9801-0	24	62	A	1400	Triode Sect.	7591	6.3	HS-6345-0	10	89	A	5100	
Model 6000 A:	No Adapter Required.														
6LT8	6.3	EV-9321-0	10	85	A	3700	Pent. Sect.	7683	6.3	EV-1382-0	10	50	A	1250	
6LT8	6.3	EV-0807-0	0	92	D	-----	Diode No. 1	7687	6.3	EV-2637-0	10	82	A	3200	Pent. Sect.
6LT8	6.3	EV-0607-0	0	92	D	-----	Diode No. 2	7687	6.3	EV-9108-0	29	79	A	2100	Triode Sect.
6LU8†	6.3	B3-6489-0	40	87	A	4000	Pent. Sect.	7695	50.0	EV-6917-0	30	94	A	9000	
6LU8	6.3	B3-X20A-0	24	62	A	1400	Triode Sect.	7701	12.6	EV-2691-0	10	83	A	3300	
6LY8	6.3	EV-7986-0	22	85	A	3400	Pent. Sect.	7716	12.6	EV-7986-0	10	87	A	4500	Pent. Sect.
6LY8	6.3	EV-2301-0	17	48	A	1100	Triode Sect.	7716	12.6	EV-2301-0	10	69	A	1700	Triode Sect.
6M3	6.3	JS-030X-0	0	91	D	-----		7717	6.3	ET-1562-0	11	81	B	3000	
6M11†	6.3	B3-2A3X-0	11	86	A	3750	Pent. Sect.	7719	12.6	EV-2103-0	29	84	A	3500	
6M11	6.3	B3-8709-0	20	82	A	3000	Triode No. 1	7724	12.6	EV-8907-0	10	15	A	600	Triode Sect.
6M11	6.3	B3-5604-0	20	82	A	3000	Triode No. 2	7724	12.6	EV-0601-0	0	80	C	-----	Diode No. 1
6MB8	6.3	EV-9678-0	8	84	A	4000	Pent. Sect.	7724	12.6	EV-0203-0	0	80	C	-----	Diode No. 2
6MB8	6.3	EV-1203-0	13	88	A	4800	Triode Sect.	7728	12.6	EV-7608-0	11	81	A	3000	Triode No. 1
6MD8†	6.3	EV-6307-0	20	85	A	3500	TRIODE NO. 1 USE ADAPTER SA-4, 1050-144. NOTE 3	7728	12.6	EV-2103-0	11	81	A	3000	Triode No. 2
6MD8	6.3	EV-8207-0	20	85	A	3500	Triode No. 2	7729	12.6	EV-7608-0	12	58	A	1250	Triode No. 1
6MD8	6.3	EV-9107-0	20	85	A	3500	Triode No. 3	7729	12.6	EV-2103-0	12	58	A	1250	Triode No. 2
Model 6000 A:	No Adapter Required.														
6ME8	6.3	EV-6937-2	24	25	A	700	Plate No. 1	7730	12.6	EV-7608-0	24	75	A	2200	Triode No. 1
6ME8	6.3	EV-6837-2	24	25	A	700	Plate No. 2	7730	12.6	EV-2103-0	24	75	A	2200	Triode No. 2
6MF8†	6.3	B3-7489-0	30	84	A	4000	Pent. Sect.	7731	6.3	EV-2637-0	11	73	A	2000	Pent. Sect.
6MF8	6.3	B3-X20A-0	23	66	A	1900	Triode Sect.	7731	6.3	EV-9108-0	12	90	A	6200	Triode Sect.
6MJ8†	6.3	B3-A203-0	27	78	A	2800	Triode No. 1	7732	6.3	ET-1562-7	11	81	A	3000	
6MJ8	6.3	B3-X403-0	27	78	A	2800	Triode No. 2	7733	12.6	EV-2781-3	11	87	A	4500	
6MJ8	6.3	B3-8603-0	27	78	A	2800	Triode No. 3	7734	6.3	EV-8917-0	14	72	A	1850	Pent. Sect.
6MK8	6.3	EV-7821-9	11	30	F	-----	Pent. No. 1	7734	6.3	EV-3602-0	64	86	A	4700	Triode Sect.
6MK8	6.3	EV-7321-6	11	30	F	-----	Pent. No. 2	7737	6.3	EV-2791-8	11	81	A	3000	
6MN8†	6.3	B3-8603-0	25	68	A	1850	Triode No. 1	7738	6.3	ET-2105-0	13	89	A	5500	
6MN8	6.3	B3-X403-0	25	68	A	1850	Triode No. 2	7754	6.3	EV-6917-0	30	94	A	9000	
6MN8	6.3	B3-A203-0	25	68	A	1850	Triode No. 3	7757	6.3	DV-6X78-0	11	86	A	4100	
6MQ8	6.3	EV-2637-0	15	80	A	3000	Pent. Sect.	7759	25.0	DW-7805-0	25	78	A	2500	Triode No. 1
6MQ8	6.3	EV-9108-0	20	83	A	3300	Triode Sect.	7759	25.0	DW-2104-0	25	78	A	2500	Triode No. 2
6Q11†	6.3	B3-9X04-8	24	75	A	2200	Triode No. 1	7760	25.0	DW-7805-0	36	73	A	2000	Triode No. 1
6Q11	6.3	B3-7506-8	12	58	A	1250	Triode No. 2	7760	25.0	DW-2104-0	36	73	A	2000	Triode No. 2
6Q11	6.3	B3-A203-8	12	58	A	1250	Triode No. 3	7761	25.0	DW-1572-0	15	87	A	4700	
6R4	6.3	EV-1803-0	24	85	A	4000		7762	25.0	DW-1572-0	40	86	A	4200	
6S4	6.3	EV-6902-0	22	86	A	4150		7802	6.3	HY-4506-2	45	93	A	9500	Triode No. 1
6SN7	6.3	HY-4506-0	23	79	A	2600	Triode No. 1	7802	6.3	HY-1203-5	45	93	A	9500	Triode No. 2
6SN7	6.3	HY-1203-0	23	79	A	2600	Triode No. 2	7803	6.3	EV-7608-0	22	91	A	7000	Triode No. 1
6T4	6.3	ET-2105-0	36	88	A	5000		7803	6.3	EV-2103-0	22	91	A	7000	Triode No. 2
6T8	6.3	EV-8907-0	11	56	A	1200	Triode Sect.	7861	12.6	KR-7608-0	17	88	A	5000	Triode No. 1
6T8	6.3	EV-0607-0	0	77	C	-----	Diode No. 1	7861	12.6	KR-3402-0	17	88	A	5000	Triode No. 2
6T8	6.3	EV-0203-0	0	77	C	-----	Diode No. 2	7867	6.3	HS-5X83-0	23	93	B	9000	
6T8	6.3	EV-0107-0	0	77	C	-----	Diode No. 3	7868†	6.3	EV-2973-0	18	89	A	5200	USE ADAPTER SA-4, 1050-144. NOTE 3
6T9†	6.3	B3-8AX9-0	15	87	A	4500	Pent. Sect.	Model 6000 A:	No Adapter Required.						
6T9	6.3	B3-4205-0	19	36	A	950	Triode Sect.	7889	25.0	DW-7805-0	20	65	A	1500	Triode No. 1
6T10†	6.3	B3-8AX9-0	19	88	A	4500	Pent. No. 1	7889	25.0	DW-2104-0	20	65	A	1500	Triode No. 2
								7895†	6.3	DR-4208-0	22	82	A	3200	USE ADAPTER SA-3, 1050-127. NOTE 3
								Model 6000 A:							
								7895	6.3	13-4208-0	22	82	A	3200	

6T8	6.3	EV-0607-0	0	77	C	-----	Diode No. 1	Model 6000 A:	No Adapter Required.										
6T8	6.3	EV-0203-0	0	77	C	-----	Diode No. 2	7889	25.0	DW-7805-0	20	65	A	1500	Triode No. 1				
6T8	6.3	EV-0107-0	0	77	C	-----	Diode No. 3	7889	25.0	DW-2104-0	20	65	A	1500	Triode No. 2				
6T9†	6.3	B3-8AX9-0	15	87	A	4500	Pent. Sect.	7895†	6.3	DR-4208-0	22	82	A	3200	USE ADAPTER SA-3, 1050-127, NOTE 3.				
6T9	6.3	B3-4205-0	19	36	A	950	Triode Sect.	Model 6000 A:											
6T10†	6.3	B3-8AX9-0	19	88	A	4500	Pent. No. 1	7895	6.3	13-4208-0	22	82	A	3200					
6T10	6.3	B3-3762-5	14	21	B	625	Pent. No. 2	7898	6.3	EV-7608-0	11	86	A	4000	Triode No. 1				
6U8	6.3	EV-2637-0	11	73	A	2000	Pent. Sect.	7898	6.3	EV-2103-0	11	86	A	4000	Triode No. 2				
6U8	6.3	EV-9108-0	12	90	A	6200	Triode Sect.	7905	6.3	KR-2680-7	10	88	A	4650					
6U9†	6.3	FW-3782-4	10	83	A	3300	PENT. SECT. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3	7984†	12.6	B3-X3A9-0	42	87	A	4050					
6U9	6.3	FW-X901-0	29	81	A	3000	Triode Sect.	7995	6.3	ER-3782-6	13	82	A	3100					
6U10†	6.3	B3-9X04-0	26	74	A	1900	Triode No. 1	8032	12.6	HS-5X31-8	45	88	A	5000					
6U10	6.3	B3-7506-0	19	14	A	575	Triode No. 2	8056†	6.3	DR-0208-4	0	68	C	-----	OK ABOVE 1300 ON 3000 SCALE USE ADAPTER SA-3, 1050-127, NOTE 3				
6U10	6.3	B3-A203-0	26	74	A	1900	Triode No. 3	Model 6000 A:											
6V3	6.3	EV-020X-0	0	88	D	-----		8056	6.3	13-0208-4	0	68	C	-----	OK ABOVE 1300 ON 3000 SCALE JUMPER SHELL TO PIN 5 OF OCTAL SOCKET USE ADAPTER SA-3, 1050-127, NOTE 3				
6V5	6.3	HY-5340-0	40	86	A	4100		8058†	6.3	DR-5X02-0	19	85	A	3800					
6V6	6.3	HS-5348-1	13	86	A	4100		Model 6000 A:											
6V9†	6.3	FW-3741-2	10	48	B	1000	HEPT. SECT. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3	8058	6.3	13-5102-0	19	85	A	3800					
6V9	6.3	FW-8X09-0	22	81	A	3000	Triode Sect.	"Do not use tester cap connector. Jumper tube cap to Pin 1 of octal socket. Jumper shell to Pin 5 of novar socket."											
6W4	6.3	HY-0503-0	0	88	D	-----		8064	25.0	DW-1578-0	15	75	A	2150					
6W6	6.3	HS-5348-0	11	91	B	7500		8068	6.3	HS-5X83-0	15	90	A	7000					
6X4	6.3	ET-0607-1	0	40	D	-----	Plate No. 1	8077	12.6	EV-2781-3	11	87	A	4500					
6X4	6.3	ET-0107-6	0	40	D	-----	Plate No. 2	8084	12.6	DU-1562-7	18	81	A	3000					
6X5	6.3	HS-0508-1	0	50	D	-----	Plate No. 1	8096	6.3	GX-2105-0	20	53	A	1100					
6X5	6.3	HS-0308-1	0	50	D	-----	Plate No. 2	8102	12.6	EV-9678-0	11	81	A	3000	Pent. Sect.				
6X8	6.3	EV-7986-1	12	81	A	3000	Pent. Sect.	8102	12.6	EV-3102-0	21	85	A	3900	Triode Sect.				
6X8	6.3	EV-2306-1	20	84	A	3500	Triode Sect.	8106	12.6	EV-7189-0	16	87	A	4450					
6X9†	6.3	FW-3782-4	10	84	A	3600	PENT. SECT. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3	8113	6.3	ET-1567-0	22	82	A	2600					
6X9	6.3	FW-X901-0	12	81	A	3000	Triode Sect.	8136	6.3	ET-1562-7	12	83	A	3300					
6Y9†	6.3	FW-8X97-0	13	88	A	5000	PENT. NO. 1. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3	8149†	12.6	B3-X789-0	44	88	A	4500					
6Y9	6.3	FW-1432-0	13	83	A	3300	Pent. No. 2	8150†	12.6	B3-X386-0	44	88	A	4500	CAP-P. JUMPER FROM PIN 3 TO CAP				
6Y10†	6.3	B3-8AX9-0	20	86	A	4000	Pent. No. 1	8156†	12.6	B3-X376-0	25	90	A	5000					
6Y10	6.3	B3-3762-5	12	67	A	1600	Pent. No. 2	8185	6.3	JR-2306-0	25	87	A	4300					
6Z4	6.3	FR-0304-0	0	60	D	-----	Plate No. 1	8186	25.0	JR-2306-0	25	87	A	4300					
6Z4	6.3	FR-0204-0	0	60	D	-----	Plate No. 2	8203†	6.3	DR-4208-0	29	78	A	2400	USE ADAPTER SA-3, 1050-127, NOTE 3				
6Z10†	6.3	B3-7468-5	6	27	B	700	Pent. No. 1	Model 6000 A:											
6Z10	6.3	B3-A923-0	16	88	A	4350	Pent. No. 2	8203	6.3	13-4208-0	29	78	A	2400					
7AU7	6.3	EV-7608-0	24	75	A	2200	Triode No. 1	8236	6.3	HS-1X43-0	43	92	A	7800					
7AU7	6.3	EV-2103-0	24	75	A	2200	Triode No. 2	8298	6.3	HS-5X31-8	23	90	A	8000					
7DJ8	7.5	EV-7608-0	22	91	A	7000	Triode No. 1	8327	6.3	EV-2793-0	23	92	A	5500					
7DJ8	7.5	EV-2103-0	22	91	A	7000	Triode No. 2	8334	6.3	ET-6705-0	14	89	A	6000					
7EY6	7.5	HS-5348-0	28	87	A	4400		8393†	12.6	DR-4208-0	27	85	A	3700	USE ADAPTER SA-3, 1050-127, NOTE 3				
7HG8	7.5	EV-2893-0	10	84	A	3600	Pent. Sect.	Model 6000 A:											
7HG8	7.5	EV-6703-0	32	82	A	3200	Triode Sect.	8393	12.6	13-4208-0	27	85	A	3700					
7KY6	7.5	EV-2781-3	17	88	A	5000		8417	6.3	HS-5348-0	10	93	A	10000					
7KZ6	7.5	EV-2781-3	17	88	A	5000		8431	12.6	EV-7608-0	18	93	A	5500	Triode No. 1				
8AC9†	7.5	B3-9AX8-7	10	87	A	4200	Pent. Sect.	8431	12.6	EV-2103-0	18	93	A	5500	Triode No. 2				
8AC9	7.5	B3-0304-0	0	85	C	-----	Diode No. 1	8445	6.3	EV-2637-0	10	84	A	3500	Pent. Sect.				
8AC9	7.5	B3-0203-0	0	85	C	-----	Diode No. 2	8445	6.3	EV-9108-0	20	84	A	3500	Triode Sect.				
8AC10†	10.0	B3-9X04-0	10	80	A	3000	TRIODE NO. 1. MAKE "LINE TEST" AT 1240 ON 3000 SCALE.	8446	6.3	EV-9678-0	10	82	A	3000	Pent. Sect.				
8AC10	10.0	B3-7506-0	10	80	A	3000	Triode No. 2	8446	6.3	EV-1203-0	14	87	A	4000	Triode Sect.				
8AC10	10.0	B3-X203-0	10	80	A	3000	Triode No. 3	8489	6.3	EV-8679-0	10	84	A	3600	Pent. Sect.				
8AL9†	7.5	B3-A2X9-4	5	91	A	9000	Pent. Sect.	8489	6.3	EV-2103-0	20	85	A	3800	Triode Sect.				
8AL9	7.5	B3-5706-0	9	88	A	6300	Triode Sect.	8532	6.3	ET-1702-0	20	90	A	6000					
								8552	12.6	HS-5X31-8	23	91	A	7000					
								8628†	6.3	BT-4208-0	12	0	A	500	USE ADAPTER SA-3, 1050-127, NOTE 3				
								Model 6000 A:											
								8628	6.3	13-4208-0	12	0	A	500					

Roll Chart provided free at StevenJohnson.com. Not for resale in any form.

6Y9	6.3	FW-1432-0	13	83	A	3300	Pent. No. 2
6Y10†	6.3	B3-8AX9-0	20	86	A	4000	Pent. No. 1
6Y10	6.3	B3-3762-5	12	67	A	1600	Pent. No. 2
6Z4	6.3	FR-0304-0	0	60	D	-----	Plate No. 1
6Z4	6.3	FR-0204-0	0	60	D	-----	Plate No. 2
6Z10†	6.3	B3-7468-5	6	27	B	700	Pent. No. 1
6Z10	6.3	B3-A923-0	16	88	A	4350	Pent. No. 2
7AU7	6.3	EV-7608-0	24	75	A	2200	Triode No. 1
7AU7	6.3	EV-2103-0	24	75	A	2200	Triode No. 2
7DJ8	7.5	EV-7608-0	22	91	A	7000	Triode No. 1
7DJ8	7.5	EV-2103-0	22	91	A	7000	Triode No. 2
7EY6	7.5	HS-5348-0	28	87	A	4400	
7HG8	7.5	EV-2893-0	10	84	A	3600	Pent. Sect.
7HG8	7.5	EV-6703-0	32	82	A	3200	Triode Sect.
7KY6	7.5	EV-2781-3	17	88	A	5000	
7KZ6	7.5	EV-2781-3	17	88	A	5000	
8AC9†	7.5	B3-9AX8-7	10	87	A	4200	Pent. Sect.
8AC9	7.5	B3-0304-0	0	85	C	-----	Diode No. 1
8AC9	7.5	B3-0203-0	0	85	C	-----	Diode No. 2
8AC10†	10.0	B3-9X04-0	10	80	A	3000	TRIODE NO. 1. MAKE "LINE TEST" AT 1240 ON 3000 SCALE.
8AC10	10.0	B3-7506-0	10	80	A	3000	Triode No. 2
8AC10	10.0	B3-X203-0	10	80	A	3000	Triode No. 3
8AL9†	7.5	B3-A2X9-4	5	91	A	9000	Pent. Sect.
8AL9	7.5	B3-5706-0	9	88	A	6300	Triode Sect.
8AR11†	7.5	B3-X89A-7	10	81	A	2700	Pent. No. 1
8AR11	7.5	B3-5236-4	10	81	A	2700	Pent. No. 2
8AU8	7.5	EV-7986-0	11	86	A	4200	Pent. Sect.
8AU8	7.5	EV-2301-0	15	86	A	4000	Triode Sect.
8AV11†	7.5	B3-9X04-0	22	78	A	2500	Triode No. 1
8AV11	7.5	B3-7506-0	22	78	A	2500	Triode No. 2
8AV11	7.5	B3-A203-0	22	78	A	2500	Triode No. 3
8AW8A	7.5	EV-7986-0	10	88	A	5000	Pent. Sect.
8AW8A	7.5	EV-2301-0	15	78	A	2500	Triode Sect.
8B10†	7.5	B3-5607-0	28	75	A	2000	TRIODE NO. 1. MAKE "LINE TEST" AT 1700 ON 3000 SCALE.
8B10	7.5	B3-3402-0	28	75	A	2000	Triode No. 2
8B10	7.5	B3-0X09-0	0	76	C	-----	Diode No. 1
8B10	7.5	B3-0809-0	0	76	C	-----	Diode No. 2
8BA8A	7.5	EV-7986-0	11	88	A	5000	Pent. Sect.
8BA8A	7.5	EV-2301-0	30	79	A	2700	Triode Sect.
8BA11†	7.5	B3-4638-7	10	15	A	600	Pent. No. 1
8BA11	7.5	B3-4238-5	10	15	A	600	Pent. No. 2
8BA11	7.5	B3-9A0X-0	30	62	A	1600	Triode Sect.
8BH8	7.5	EV-7986-0	7	88	A	5000	Pent. Sect.
8BH8	7.5	EV-2301-0	27	83	A	3000	Triode Sect.
8BM11†	7.5	B3-A79X-8	10	85	A	3700	Pent. No. 1
8BM11	7.5	B3-6235-4	13	84	A	3500	Pent. No. 2

©THE HICKOK ELECTRICAL INSTRUMENT COMPANY, CLEVELAND, OHIO, 1970

PRINTED IN U. S. A.

STOP

FALL 1970

Model 6000-6000A-

8186	6.3	JR-2306-0	25	87	A	4300	
8203†	6.3	DR-4208-0	29	78	A	2400	USE ADAPTER SA-3, 1050-127. NOTE 3
Model 6000 A:							
8203	6.3	13-4208-0	29	78	A	2400	
8236	6.3	HS-1X43-0	43	92	A	7800	
8298	6.3	HS-5X31-8	23	90	A	8000	
8327	6.3	EV-2793-0	23	92	A	5500	
8334	6.3	ET-6705-0	14	89	A	6000	
8393†	12.6	DR-4208-0	27	85	A	3700	USE ADAPTER SA-3, 1050-127. NOTE 3
Model 6000 A:							
8393	12.6	13-4208-0	27	85	A	3700	
8417	6.3	HS-5348-0	10	93	A	10000	
8431	12.6	EV-7608-0	18	93	A	5500	Triode No. 1
8431	12.6	EV-2103-0	18	93	A	5500	Triode No. 2
8445	6.3	EV-2637-0	10	84	A	3500	Pent. Sect.
8445	6.3	EV-9108-0	20	84	A	3500	Triode Sect.
8446	6.3	EV-9678-0	10	82	A	3000	Pent. Sect.
8446	6.3	EV-1203-0	14	87	A	4000	Triode Sect.
8489	6.3	EV-8679-0	10	84	A	3600	Pent. Sect.
8489	6.3	EV-2103-0	20	85	A	3800	Triode Sect.
8532	6.3	ET-1702-0	20	90	A	6000	
8552	12.6	HS-5X31-8	23	91	A	7000	
8628†	6.3	BT-4208-0	12	0	A	500	USE ADAPTER SA-3, 1050-127. NOTE 3
Model 6000 A:							
8628	6.3	13-4208-0	12	0	A	500	

NEITHER THIS CHART NOR ANY PART THEREOF MAY BE COPIED WITHOUT PERMISSION OF THE COPYRIGHT OWNER.

STOP

FALL 1970

6005 Tube Testers